


AUDIO ENGINEERING

AUGUST
1949
35c



Including

The Journal of the
AUDIO engineering society

www.americanradiohistory.com



NO MORE HOT-WEATHER PROBLEMS

...when you



record on **audiodiscs***

To the recordist, the hot, summer months have generally meant plenty of trouble—not because of the heat, but due to the accompanying high humidity. For moisture which is absorbed by the lacquer of a recording disc has a serious effect on the cutting characteristics. The noise level increases progressively while recording, and the cut gets greyer and greyer. This problem has affected the entire lacquer disc industry. But, with Audiodiscs, it is a problem no longer. You can now record as well on the hottest and dampest day as you could on a crisp day in fall or winter.

This freedom from humidity troubles is the result of an exclusive Audiodisc improvement perfected in 1947. It is an improvement which goes far beyond the control of atmospheric conditions during manufacture—for that alone doesn't prevent moisture absorp-

tion later on. The moisture problem has been solved at its most vulnerable point—in the lacquer itself!

By the addition of a special moisture resisting agent—without any change in the basic formulation—Audiodisc lacquer has been made *permanently* resistant to humidity. Its outstanding “all weather” performance has been proved by countless tests in our “weather room”, under the most severe conditions of temperature and humidity. But the most conclusive proof of all has come from the field. For, during the summer of 1948, one of the most humid on record, none of our customers have reported any difficulties in recording or reproduction due to moisture conditions.

See for yourself what a big difference this improvement can make in *your* summer recordings. Ask your dealer for Audiodiscs!

Audiodiscs are manufactured in the U.S.A. under exclusive license from PYRAL, S.A.R.L., Paris

AUDIO DEVICES, INC.

444 MADISON AVE., NEW YORK 22, N. Y.

*Reg. U.S. Pat. Off.

EXPORT DEPT.: ROCKE INTERNATIONAL, 13 EAST 40TH ST., NEW YORK 16, N. Y.



RADIO-TELEFAX UNITS WITH SYLVANIA TUBES


SPREAD THE NEWS OF INCOMING SHIPS!



Pilot boat Captain sending written message of arrival of the big ship through Link unit equipped with Sylvania tubes, and in short order . . .

★ ★ ★

. . . message arrives in Western Union Marine News room as facsimile reproduction, then is transmitted by an operator and simultaneously appears on tickers at offices of newspapers, customs, postal and immigration authorities, taxi, steamship companies and many others.



Link radio equipment used in Western Union Marine Reporting Service

RADIO-TELEFAX, a new type of telegraph communication, reports ship arrivals as part of Western Union's Marine Reporting Service.

Out at sea, the captain of the New York Pilot Boat spots incoming liners, writes a message such as "SS QUEEN ELIZABETH INCOMING AT 1644" on a telegraph blank and inserts it in an automatic Telefax transmitter. The unit then transmits it to Western Union over a VHF radio channel. It arrives as a *facsimile* of the sent message!


And inside this Link equipment, rugged Sylvania tubes, operating smoothly, do their part in this

important marine reporting service. Find out more about the complete Sylvania line of Radio Tubes . . . see your Sylvania Distributor or write Radio Tube Division, Emporium, Pa.

SYLVANIA ELECTRIC

RADIO TUBES; CATHODE RAY TUBES; ELECTRONIC DEVICES; FLUORESCENT LAMPS, FIXTURES, WIRING DEVICES; LIGHT BULBS; PHOTOLAMPS

AUDIO ENGINEERING ● AUGUST, 1949



VOLTAGE RANGE:

3,000,000 to 1

READINGS:

.1 mv to 300 v

FREQUENCIES:

20 cps to 2 mc

THE NEW *-hp-* 400C VACUUM TUBE VOLTMETER

Increased sensitivity. Wider range. Easy-to-read linear scale. Space-saving, time-saving versatility! Those are but a few of the many advantages of the new *-hp-* 400C Vacuum Tube Voltmeter.

30 times more sensitive than the *-hp-* 400A voltmeter, the new *-hp-* 400C accurately determines voltages from .1 mv to 300 v. Its measuring range is broad and new—3,000,000 to 1. And with it you can make split-hair measurements all the way from 20 cps to 2 mc!

The big, clearly-calibrated linear scale reads directly in RMS volts or db based on 1 mw into 600 ohms. Generous overlap makes possible more readings at mid or maximum scale, where accuracy is highest. A new output terminal lets you use the *-hp-* 400C as a wide-band stabilized amplifier, for increasing gain of oscilloscopes, recorders and measuring devices. As a voltmeter, the new instrument has still wider applicability—for direct hum or noise readings, transmitter and receiver voltages, audio, carrier or supersonic voltages, power gain or network response.

Naturally the new *-hp-* 400C includes the familiar advantages of the *-hp-* 400A voltmeter. Range switch is calibrated in 10 db intervals providing direct readings from -70 dbm to +52 dbm. Overall accuracy

is $\pm 3\%$ full scale to 100 kc. High input impedance of 1 megohm means circuits under test are not disturbed. And the rugged meter movement is built to safely withstand occasional overloads 100 times normal.

In every respect, the convenient, durable *-hp-* 400C is the ideal new voltmeter for precision work in laboratory, plant or repair shop. Complete details are available at no obligation. Write today!

Hewlett-Packard Company

1556L Page Mill Road, Palo Alto, California
Export Agents: Frazar & Hansen, Ltd.
301 Clay Street, San Francisco, Calif., U.S.A.

CHECK THESE SPECIFICATIONS

VOLTAGE RANGES:

12 ranges. Full-scale readings.

.001 v	.100 v	10.0 v
.003 v	.300 v	30.0 v
.010 v	1.00 v	100. v
.030 v	3.00 v	300. v

FREQUENCY RANGE: 20 cps to 2 mc

ACCURACY:

$\pm 3\%$ full scale 20 cps to 100 kc
 $\pm 5\%$ full scale 100 kc to 2 mc

INPUT IMPEDANCE:

10 megohms shunted by 15 uufd on 1.0 v to 300 v ranges, 25 uufd on the .001 v to .300 v ranges.

METER SCALE:

3" linear. Voltage ranges related by 10 db steps. Db calibrated -12 to +2 db. Zero level 1 mw into 600 ohms.

OUTPUT CIRCUIT:

Maximum 0.5 v full scale. Internal impedance 1000 ohms.

POWER SUPPLY:

115 v, 50/60 cps, 45 watts.

CABINET SIZE:

hp laboratory instruments
FOR SPEED AND ACCURACY

Power Supplies Frequency Standards Amplifiers Electronic Tachometers Frequency Meter
UHF Signal Generators Square Wave Generators Audio Frequency Oscillators Attenuators
Audio Signal Generators Noise and Distortion Analyzers Wave Analyzers Vacuum Tube Voltmeter



Successor to **RADIO**

D. S. Potts, Publisher

C. G. McProud, Editor

Louisa B. DeSoto, Edit. Prod. Mgr.

S. L. Cahn, Adv. Director

David Saltman, Production Manager

H. N. Reizes, Adv. Mgr.

E. E. Newman, Circulation Manager

L. B. Devine, Asst. Circ. Mgr.

Editorial Advisory Board

Howard A. Chinn

John D. Colvin

C. J. LeBel

J. P. Maxfield

George M. Nixon

Winston Wells

S. Young White

Representatives

Sanford R. Cowan, Mid-West Sales
342 Madison Ave., New York 17, N. Y.

James C. Galloway, Pacific Coast Sales
816 W. 5th St., Los Angeles 13, Calif.

Dale International Publications, Ltd.
106 Bolsover St., London W. 1, England

Technical Book & Magazine Co.,
297 Swanston St., Melbourne C. I.
Victoria, Australia

Established 1917

CONTENTS

AUGUST, 1949

Vol. 33, No. 8

Editor's Report	6
Letters	8
Book Review	8
New Developments in Cathode Followers— <i>C. J. LeBel</i>	11
Magnetic Tape Erasure by Permanent Magnets— <i>Robert Herr</i>	14
Low-Cost Precision Magnetic Recorder for Professional Use— <i>Myron J. Stolaroff</i>	17
Problems in Audio Engineering, Part IV— <i>Lewis S. Goodfriend</i>	19
Record Revue— <i>Edward Tatnall Canby</i>	21
The Journal of the Audio Engineering Society	
Message from the President	22
Coming to the Audio Fair?	22
Employment Service	22
New Electronic Audio Sweep-Frequency Generator— <i>H. Toomin</i>	23
Techni-Briefs—Tubeless "Hi-Fi" Tuner	32
New Products	39
Advertising Index	40

COVER

Photomontage of a human ear (the ear of a six-months-old baby) and a plastic model of the middle and inner ear structures, superimposed on an illuminated disc record. Prepared especially for Audio Engineering by John D. Goodell.

AUDIO ENGINEERING (title registered U. S. Pat. Off.) is published monthly at New York, N. Y., by Radio Magazines, Inc., D. S. Potts, President; Lawrence LeKashman, Vice Pres. Executive and Editorial Offices at 342 Madison Avenue, New York 17, N. Y. Subscription rates—United States, U. S. Possessions and Canada, \$3.00 for 1 year, \$5.00 for 2 years; elsewhere \$4.00 per year. Single copies 35c. Printed in U. S. A. All rights reserved. Entire contents copyright 1949 by Radio Magazines, Inc. Entered as Second Class Matter July 29, 1948 at the Post Office, New York, N. Y., under the Act of March 3, 1879.

EDITOR'S REPORT

THE AUDIO FAIR

TO THE AUDIO ENGINEER, the biggest news of the month is the announcement of The Audio Fair to be held October 27, 28, and 29, at Hotel New Yorker, in New York City. Long an orphan in radio-electronics, audio is rapidly becoming recognized as a separate field. With its own exhibit for the first time, this recognition is clinched.

By its very nature, audio equipment must be heard as well as seen—thus differing from the children in the old adage. Only by the use of separate rooms for the demonstration of equipment can the exhibitee be shown—both aurally and visually—the features and performance characteristics of amplifiers, speakers, recorders, microphones, and other components designed to appeal to the auditory senses. The exhibitor acceptance of The Audio Fair has been gratifying, and those who attend are assured of a full coverage of the newest equipment.

Held in conjunction with the first annual convention of the Audio Engineering Society, with several sessions of technical papers, The Audio Fair becomes a milestone in the progress of a new field.

THE NEW JOURNAL

As a result of an election by the members of the Audio Engineering Society, a new section is included in this issue under the aegis of the Society. The Journal of the Audio Engineering Society will be a regular monthly feature of the magazine, and will contain papers presented at various section meetings and at the Convention to be held in October. The first of these papers—already distributed to the members—describes an interesting electronic development in audio measuring apparatus. Next month's Journal paper will describe the well established lateral feedback recording cutter of Bell Telephone Laboratories development. These papers are published in the magazine approximately two months after their distribution to the members in individual folders, thus providing subscribers with the same material available to the members, but at a later date.

We are pleased at our selection as the medium for

the publication of the Society's papers, and we pledge our continued presentation of the best available articles on the wide field covered by the term *audio*, which must include psychoacoustics, electronics, architectural acoustics, and system design.

MORE STANDARDIZATION


Following our discussion of this subject in the two preceding issues, we are reminded of the activities of several standardization groups who have done commendable work in direction over the past years. These standards have covered practically all broadcast amplifier equipment, and microphones have been standardized just recently.

Most engineers in audio work with broadcast and recording organizations know these standards, and have been working with them since their adoption. But the importance of any standard—regardless of by whom promulgated—lies not in its acceptance by a few, but rather by its universal acceptance. The independent engineer who designs and installs a high-quality public address system far from any broadcast center must know and adhere to these standards if they are to be of the greatest benefit. Even the individual who constructs for himself—as a hobby—a home reproducing system which is equivalent in performance to a broadcast station should also have access to and should follow the standards.

To this end it is desirable that the standards be given the widest possible distribution, and they be made available to anyone who wishes them. If for no other reasons, the saving in cost to manufacturer, jobber, and user should be appreciable because of the reduction of the number of types of equipment required to cover the needs.

The fact that standards exist should certainly reflect credit to those who have been charged with the many hours of committee work, the interminable letter writing, and the inevitable discussions which arise when differing opinions must be adjusted to come out with one specific set of standards. Standards are not plucked, ready-made, from the sky—they represent years of experience and a keen analysis by competent engineers.

DELTAMAX *-now available!*



Where can YOU use a Magnetic Material with these specialized, dependable characteristics?

The properties of Deltamax are invaluable for many electronic applications, such as new and improved types of mechanical rectifiers, magnetic amplifiers, saturable reactors, peaking transformers, etc. This new magnetic material is available now as "packaged" units (cased cores ready for winding and final assembly) distributed by the Arnold organization. Every step in manufacture has been fully developed; designers can rely on

complete consistency in each standard size of core.

Deltamax is the most recent extension of the family of special, high-quality electrical materials produced by Allegheny Ludlum, steel-makers to the electrical industry. It is an orientated 50% nickel-iron alloy, characterized by a rectangular hysteresis loop with sharply defined knees, combining high saturation with low coercivity.

● Call on us for technical data.



THE ARNOLD ENGINEERING COMPANY

SUBSIDIARY OF ALLEGHENY LUDLUM STEEL CORPORATION

147 EAST ONTARIO STREET, CHICAGO 11, ILLINOIS

W40 2379



Triad Transformers

Now Stocked by Distributors

Formerly Available Only as Components of Fine Electronic Equipment




ORIGINAL EQUIPMENT—TRIAD 'HS' transformers for original equipment embody superior techniques in transformer design and construction—*power transformers* of low temperature rise and good regulation—*chokes* of low resistance and high inductance—*audio transformers* of wide range both in frequency response and in power-handling capacity. Such transformers deserve the best in mechanical construction and protection against failure as exemplified by TRIAD's perfected hermetic sealing. Quantity production of hermetically sealed transformers for our Armed Services under JAN specifications has resulted in improved production techniques, and has lowered costs on these exceptionally long-lived units to permit their use in quality electronic apparatus.



REPLACEMENT—TRIAD is a major source of transformers for radio and television manufacturers. TRIAD replacement transformers, therefore, incorporate many parts and features to make them readily and universally adaptable to vacant spots in these chassis. Features include: High-quality materials, permitting small size without excessive temperature rise; vacuum varnish impregnation of both coil and core, copper foil static shields in all power coils, heavy drawn steel cases with sturdy baked enamel finish, and high temperature UL approved lead materials.



GEOPHYSICAL—TRIAD "Geoformers" are individually calibrated components for incorporation in 5-500 cycle measuring equipment of laboratory precision. Inductance is held within $\pm 5\%$ for the entire production and frequently within $\pm 2\%$ for any given shipment of transformers. "Geoformers" incorporate hum-bucking coils and multiple alloy shielding for minimum pickup; are of minimum size and weight, and are vacuum-filled and hermetically sealed. Designs are based on years of specialization in this difficult field by pioneers in geophysical transformer design. Standard designs for use in the most used circuits are carried in stock at the factory and by TRIAD distributors. Complete specifications for "Geoformers" are given in TRIAD Bulletin GP-49, available on request.



AMATEUR—TRIAD "DX'er" line of amateur transformers have been built around high-production, low-cost, transformer parts and simple coil constructions. This permits designs employing liberal quantities of high-quality material, at reasonable cost. Simple one-purpose designs with drawn steel cases and flexible leads eliminate much of the unnecessary cost involved in heavy castings and expensive tapped coil constructions, while still permitting extensive use of finest materials essential to good transformer design.

Write for Triad Transformer Catalog TR-49. Some territories still open for qualified manufacturers' agents.

BOOTH 74

5th Annual Pacific Electronic Exhibit

August 30, 31 and September 1

San Francisco Civic Auditorium



TRIAD

TRANSFORMER MFG. CO.

2254 SEPULVEDA BLVD. • LOS ANGELES 25, CALIFORNIA



— Letters —

Microphones

Sir:

I must admit being surprised on reading your report on "New Microphone Designs" in the July issue. Not because of the comments on the desirability of providing new and better microphones but because of the inference that presently available instruments produce far more acceptable sound quality when operated under normal radio conditions than at distances required in television by camera placement.

TV undoubtedly poses new problems in sound pick-up. However, the problem of locating the microphone outside the field of vision of the camera is not new and would seem to be fundamentally the same problem the motion picture industry has handled so well. The sound perspective and over-all naturalness they achieve is refreshing after exposure to the excessive sibilance, characteristic of close radio pick-ups.

In the opinion of this reader the microphone technique of the radio industry, particularly in speech pick-up, has been an important factor in the retention of low-fidelity equipment. It would be a boon to radio, TV and PA if the microphone, when in use, could not be approached closer than thirty inches.

Coke Flannagan
Mountain Lakes, N. J.
110 Lake Drive

Book Review


Electrical Transmission of Power and Signals, by E. W. Kimbark, Professor of Electrical Engineering Northwestern University. John Wiley & Sons, Inc., New York. \$6.00.

This textbook presents a study of power, telephone, and u.h.f. transmission approached through classical transmission-line theory. To audio engineers as a group, this treatment will seem unfamiliar because it is not one which is usually employed in the study of communication circuits. However, with transmission lines assuming greater importance with the expansion of a.c. application, the studious-minded engineer will find that the rigorous presentation in this book provides a better groundwork for the comprehension of general circuit theory.

Transmission-line theory can be applied to the analysis of filters and other recurrent networks, and it has long been recognized that it is possible to evaluate performance of any network or circuit simply by a study of the passage of a unit pulse through the system. This is clearly presented by Dr. Kimbark, and the book is cited as desirable for the engineer who wishes advanced study. It is definitely not suitable for the beginner, nor was it intended as such.

Transmission-line (hyperbolic function) charts and a number of tables and graphs of the characteristics of various types of transmission lines and cables are included, and the methods of use are discussed clearly and thoroughly.

How to CUT YOUR DISC DOLLAR



SOUNDCRAFT discs are made in 25 types and sizes. You don't wear your Sunday go-to-meeting clothes to work in the garden. Why use unnecessarily expensive disc grades for everything?

Unlike some brands, Soundcraft discs are all coated with the same high-fidelity lacquer. The grading differences are based on the nearness to microscopic physical perfection.

Three grades in five sizes plus single or double face, and oversize masters, are tailored to every budget.

STANDARD NET PRICES TO RADIO STATIONS AND RECORDING STUDIOS (In Standard Packages)

THE 'BROADCASTER'

A MASTER selection in instantaneous sizes for vitally important recordings.

10" Double Face	\$.84
12" " "	1.32
16" " "	2.37
10" Single Face	.54
12" " "	.90
16" " "	1.65

THESE ARE STRICTLY 'LONG HAIR' SUPER FANCY



THE 'PLAYBACK'

A standard broadcasting-quality blank record for all professional uses in radio stations, recording and motion picture studios.

10" Double Face	\$.69
12" " "	1.14
16" " "	2.07
10" Single Face	.48
12" " "	.84
16" " "	1.44

THESE ARE THE WORK A-DAY KIND THE 'NETS' LIKE. EQUAL TO THE BEST GRADES OF OTHER BRANDS



THE 'AUDITION'

A selection from the runs of "BROADCASTERS" and "PLAYBACKS" having minor physical defects outside of the recording areas.

6 1/2" Double Face	\$.27
8" " "	.42
10" " "	.60
12" " "	.93
16" " "	1.59

THESE ARE SUCH A BARGAIN! I TALK IN A WHISPER



Standard Soundcraft economy packages of only 20 discs permit stocking wide variety of grades and sizes while simultaneously holding inventory value down.

ELECTRONIC ELECTRONICS CO.



301 252 foremostradio parts distributors in principal cities and towns deliver Soundcraft discs from local stocks.

REEVES Soundcraft CORP.
10 EAST 52nd STREET • NEW YORK 22, N.Y.

MARGIN CONTROL RECORDING BOOSTS MICROGROOVE RANGE

By A. C. Travis, Jr.*

For some time now Mercury Records have carried a little notation on their record envelopes explaining that the recording was done by a special process called, "Margin Control." That many recordists are not familiar with the meaning of these words is evidenced by the fact that we have so many times been asked for an explanation. Credit for the technique goes, according to all indications, to Bob Fine of Reeves Sound Studios. An interpretation of "Margin Control" follows in the form of a quotation from the external house organ of a famous manufacturer of blank records for both master and instantaneous recording.

"It seems that one of the major tactical problems in the ten inch versus seven inch microgroove war is the problem of the crescendo (evidently an old Mexican word meaning a noise that grows so loud it wakes up the customers). Now, when one of these crescendo passages comes along in microgroove recording, naturally the cutting stylus starts beating from side to side with such ferocity, that, while it cuts, it also displaces land material sufficiently to distort the adjoining groove. The resulting echo, even with the best discs, has relegated many master recordings to the reject pile. The obvious remedy of reducing volume cuts dynamic range, but, of course, when an irresistible force meets an immovable object, something has to give. Bob Fine gave—with an idea. He runs through the original recording or live number and "scores" it by plotting VU meter readings against time. Then, using new Fairchild equipment wherein lines-per-inch are infinitely variable from approximately ninety to five hundred, he makes the master fine-line recording by monitoring the lines-per-inch so that spacing is finest on lowest passages, coarsest on loudest ones. Appearancewise this procedure makes, from a light pattern standpoint a funny looking record. For our money a disc recording, however, was always something to be more listened to than looked at. So, Mercury Records seem downright pleased with the resulting 62 db dynamic range."

"Margin Control", according to Mr. Fine, because of the inherent low noise level of the material is particularly effective with Soundcraft 'Maestro' discs. Soundcraft's triple-filtering to remove foreign matter, and Soundcraft's uniform consistency establish wide-dynamic-range microgroove recording on a predictable basis. Incidentally, Soundcraft ads, like Soundcraft discs, are equally effective either way up. Advertisement

*Vice Pres., Reeves Soundcraft Corp.

REEVES Soundcraft CORP.
10 EAST 52nd STREET • NEW YORK 22, N.Y.

PROF. SOUNDRY SAYS..

Not just the usual lacquer ingredients, but also new in gradient "X".

Not just the usual high pressure stone filters to remove microscopic matter, but also batteries of paper filter press small as 0000012.

Not just convenient filters for drying oil, but also batteries of electrostatic precipitators that even remove smoke!

THE ANALYSIS:







MINUS { FOREIGN MATTER IN LACQUER, MICROSCOPIC DUST IN DRYING AIR } EQUALS NEW IMPROVED QUIETNESS IN CUTTING

THE FORMULA:

WITH Soundcraft CLEAN CUT LINES REDUCE EXTRANEOUS NOISE!

PROPERLY COMPOUNDED RECORDING LACQUER

DISC A BETTER RECORD TO MAKE YOUR SOUNDING CONTINUOUS IMPROVEMENT DISC DOLLAR GOES INTO PATENTED PROCESS, EVERY TENTH OF A DECADE-OLD ALTY TO PAY, IS NOT SOUNDSCRAFT HAS NO ROYALTY IN ONLY TWO YEARS - ATTAINING LEADERSHIP FOR SOUNDSCRAFT DISCS




Jensen Customode

CUSTOMODE is the answer to the ever expanding requirements of audio-video equipment. Today you may install a tuner, an amplifier and a record changer with your loudspeaker. Tomorrow you can add a TV receiver, a pick-up for micro-groove records and a record cabinet. The illustrations show a few of the hundreds of possible arrangements for Home Entertainment Centers.

Designed by leading furniture stylists and acoustic engineers around a JENSEN 15-inch loudspeaker in a Bass Reflex Cabinet—the very ultimate in high-fidelity sound reproduction—CUSTOMODE is as functional as it is beautiful. Its “building block” versatility enables you to create your own layouts as you wish, when you wish.

Write today for literature and scale cut-outs. Jensen Manufacturing Company, Division of the Muter Company, 6633 South Laramie Avenue, Chicago 38, Illinois. In Canada: Copper Wire Products, Ltd., 351 Carlaw Ave., Toronto




Shown above is Shelf which provides for inclusion of TV receiver or record albums in a CUSTOMODE ensemble.

The Bridger, with its unique double-shielded input cable

C. J. LeBEL*

Loading effects of measuring instruments are readily eliminated by a novel design



Developments in Cathode Followers

OCCASIONALLY WE LIVE with a problem for so long that we stop trying to cure it, and forget that it could be solved. Measuring the operation of a high-impedance electronic circuit without changing its performance falls in this class. Included are measurements of gain, response, and distortion at intermediate points in an amplifier (such as the output of a driver stage).

Besides the matter of loading down the point to be measured, we also must not neglect the introduction of hum. In many cases we have been confronted with choice of a shielded measuring cable and excessive loading effect, or an open wire with no loading but a lot of hum pickup instead.

To see the magnitude of the problem, we examine the following data on input impedance of typical laboratory instruments:

Distortion and Noise Meter	.1 megohm	+	40 μ f
Wave Analyzer	.2 "	+	25 μ f
Vacuum Tube Voltmeter	.5 "	+	30 μ f
Oscilloscope	2 "	+	30 μ f
Pair of open test leads, 3 ft. long			20 μ f
Coaxial shielded test lead and plugs, 3 ft. long			75 μ f to 200 μ f

Input impedance is given in the form of the equivalent parallel circuit, so that the values tabulated are effectively in parallel with each other, with the connecting lead capacitance, and with

the circuit under test. For example, if we bridge a vacuum-tube voltmeter and a distortion meter across the output of a driver stage with open leads to check the origin of some distortion, we would apply 83,000 ohms and 100 μ f of loading. These values are used in the following discussion.


Effect of Instrument Loading

Effect of the resistive component of loading is apparent at a glance in the tube data book. Added after a typical pentode stage, stage gain is reduced 75 per cent, and undistorted voltage output over 50 per cent. A high- μ triode stage is less affected, for gain drops only 50 per cent, and undistorted voltage output only 45 per cent. A low- μ triode is least affected, with a reduction in gain and undistorted output voltage of 10 per cent. These figures

are not exact, and are intended only to indicate the seriousness of a condition. They make it impossible to tell exactly what the normal tube operating characteristics are. If applied across a capacitive load (a crystal hearing-aid receiver is essentially equivalent to a .0015 μ f capacitor) or if fed through a small blocking capacitor, even the frequency response may be badly altered.

Brief inspection of Fig. 1 indicates that the reactance of a small capacitor is by no means unimportant at the higher audio frequencies. A 100 μ f capacitor has a reactance of 150,000 ohms at 10 kc, and only about 100,000 ohms at 15 kc. The effect on the frequency response of a pentode or high- μ triode stage would be very great—a loss of about 10 db at 15 kc and an even greater drop in undistorted out-

Fig. 1. Reactance of small capacitors.



*Audio Instrument Co., 1947 Broadway, New York 23, N. Y.

put. Even the capacitance of open test leads would be enough to reduce gain by 3 db at 15 kc.

It is evident from these figures that we need some sort of a new translating device which will have an input resistance of many megohms and an input capacitance of a few μf , even when a three-foot shielded input cable is used. At the same time this new bridging device must have an output impedance of not over several hundred ohms, so that it may feed any reasonable length of ordinary shielded cable, and any reasonable number of measuring instruments, without change in characteristics. With all these properties, it would be a great convenience if input and output voltage were in constant ratio, and even better if they were so closely alike that the difference could be neglected. Finally, a.c. operation is a prime necessity.

The Basic Solution

It will be recalled that in a cathode follower circuit any impedance connected between grid and cathode appears between grid and ground, increased by the cathode follower action. The resistance (using a parallel form of equivalent circuit) appears at the input increased by the factor $(\mu + 1)/1$ and the capacitance appears decreased by the factor $1/(\mu + 1)$.

These are approximate relations, but they serve to illustrate the basic idea. Now the increase of resistance applies to a suitably connected grid leak, as well as to internal tube leakage, and the decrease of capacitance applies to external capacitors connected between grid and cathode, as well as to the internal tube capacitance. We can utilize this principle in the basic circuit of Fig. 2. We use a coaxial cable and re-




Fig. 2. Basic cathode follower circuit.

duce the effective capacitance between shield and central conductor by connecting the shield to the cathode of the tube.

To make the circuit practical, two changes are necessary, and one is more desirable. First, we supply grid bias by tapping down a little on the cathode resistor. Secondly, we have to shield this cable by adding a second shield

¹ It is believed that this idea was first applied in an experimental microphone circuit at Harvard University during the war.




Fig. 3. Practical cathode follower circuit.

outside the first, to eliminate hum pickup by the inner shield. Finally, we improve the ratios $(\mu + 1)/1$ and $1/(\mu + 1)$ by increasing μ . We have our choice of a high- μ triode, or a pentode, and we use the latter. The circuit changes to that of Fig. 3, which includes both actual and equivalent configurations. It can be seen that the capacitance between the central conductor and the inner shield of the cable appears between grid and cathode of the tube, but the capacitance between the inner and outer shields appears as a load across the output. Since a reactive load will tend to limit the performance of a cathode follower, this capacitance must be minimized. Inadvertently, we have gotten ourselves into a new problem in coaxial cable design.

The Cable Problem

The fundamentals of coaxial cable design are given in Fig. 4. It is apparent that low capacitance can be achieved only by minimizing the dielectric constant K and increasing the ratio D/d . When we come to the actual cable, we have one coaxial within the other, and D_1 of the inner cable becomes d_2 of the outer cable (plus a small allowance for shield thickness). We have a nice problem in design not faced by wartime designers of double-shielded cables. They were able to put the outer shield directly on top of the inner. We have to keep both D/d ratios at a reasonably high value.

The effect of varying D/d , for insulating materials of different dielectric constants, is shown in Fig. 5. It may be noted, for a dielectric constant of 2, that D/d must be about 4 to give a capacitance of 24 μf per foot. If we try to hold each capacitance to that value, then outside D /inside d will ex-

ceed 16. If we use a dielectric constant of 4, then D/d is over 10 for 24 μf per foot, and outside D /inside d will run well over 100.

The physical significance of the latter value needs to be emphasized. If we start with an inner d of .020 inches, the outer D becomes 2 inches—surely a bit large for a test cable. In the writer's own design, values of 30 μf from conductor to inner shield, and 22 μf per foot from inner shield to outer shield were used as an objective. This made it possible to achieve the small outside diameter, over the jacket, of .350 inches. A high degree of flexibility can be achieved with that outer diameter if the plastic insulation is properly formulated.

We can retain low capacitance at the cable input only if all stray capacitances are made negligible, or are guarded out by a shield driven by the cathode. As applied to the plug, this means that the outer shell is connected to cathode, not to ground. A grounded shield could be mounted on the panel, but we find that proximity of the shell




Fig. 4. Coaxial cable design.

to the case is enough to keep its hum pickup down below that of other sources of hum.

In choosing a plug and receptacle, then, we look for a perfection of shielding, not for low internal capacitances. The latter is almost all cancelled out, anyway, by the cathode follower.

Cathode Follower Design

We have designed a good cable, and chosen a satisfactory plug. It remains only to design a good cathode follower. In view of the large number of recent articles on the subject, one should have no difficulty in doing this, but a little review of fundamentals may save much reaching for the handbooks.

The internal output impedance of a cathode follower is, disregarding the cathode resistor, and to a close approximation:

$$R_{out} = 1/G_m$$

This tells us, for example, that an output impedance of 200 ohms can be achieved if we will use a tube whose transconductance is 5000 micromhos.

The input capacitance will be:

$$C_i = C_{gp} + (1 - E_o/E_i) C_{ek}$$

where E_o = output voltage
 E_i = input voltage
of follower

Remember that C_{ek} includes the cable and plug capacitance as well as the internal capacitance of the tube. This tells us that 100 $\mu\mu\text{f}$ of cable, plug, and grid to cathode capacitance can be reduced to 2 $\mu\mu\text{f}$ if we can achieve an output/input ratio of 0.98.

The input resistance will be

$$R_i = R_{gk} \frac{1}{1 - E_o/E_i}$$

This tells us that a 2-megohm grid-leak will appear as 100 megohms at the input if we can, again, achieve an output/input ratio of 0.98.

So we find that an output/input ratio of nearly unity is necessary to achieve high input impedance, as well as being convenient of itself. The formula for this ratio is

$$\frac{E_o}{E_i} = \frac{\mu Z_L}{R_p + (1 + \mu) Z_L}$$

where Z_L = load impedance

If the plate impedance R_p is very small compared to $Z_L(1 + \mu)$, then the formula can be simplified to:

$$\frac{E_o}{E_i} \approx \frac{\mu}{1 + \mu}$$

This is the form which is often cited in discussions. A little computation and experiment will mark it as a useful guide to thinking, but rather inaccurate with pentode tubes and low load impedances.

At any rate, both formulas stress the importance of high tube amplification factor. We can get this with either a high- μ triode or a pentode. If we choose a triode, we find that the highest

μ readily available is about 100, accompanied by a nominal transconductance of 1500. A new problem now enters. For a number of reasons, resistance in the cathode circuit is preferable to other coupling means. But unless we use a prohibitively high plate-supply voltage, we are likely to realize only half the data book transconductance, with resistance coupling. So we are going to end up with a transcon-

ductance of say 700, and a plate impedance of perhaps 100,000 ohms. This will give a voltage ratio of 0.94, and an output impedance of 1400 ohms. The voltage ratio is far from the 0.98 that we assumed, and we find that 100 $\mu\mu\text{f}$ of cable capacitance would look like 6 $\mu\mu\text{f}$ instead of 2 $\mu\mu\text{f}$.

We can get both higher μ and higher transconductance if we will change to a pentode. For example, a 6AC7




Fig. 5. Capacitance of a coaxial cable.





Fig. 6. Cathode follower and power supply.

Fig. 7. Frequency response of cathode follower.



Magnetic Tape Erasure by Permanent Magnets

ROBERT HERR*

Applications of d-c pulses may be used to obtain erasure almost comparable to the results possible with a-c bias, providing the conditions are carefully controlled.

FOR GOOD ERASURE of magnetic tape recordings, two requirements should be met. The first is complete obliteration of previous signals. This condition is met if, at some time in the erasing process, the magnetic material is saturated in at least one direction. The second requirement is demagnetization of the tape. This is important in order to achieve minimum background noise and minimum distortion in the subsequent recording. This condition is best met by subjecting the magnetic material to a large number of cycles of alternating fields of symmetrical waveform which at some point in the process reach substantial saturation and, thereafter, decrease gradually through many cycles to zero.

A third consideration of some practical importance is that the process be insensitive to the magnetic characteristics of the tape to be erased, so that a given erasing means may be used without change for any of a wide variety of tapes. The alternating field process, with a high enough maximum field, will work on any tape. Some permanent magnet processes will obliterate the signal from any tape, but leave various states of magnetization on various tapes.

Thus from a magnetic point of view, demagnetization by alternating fields is satisfactory, but from a manufacturing point of view it is attractive to erase tape by one or more permanent magnets because such erase offers economy, reliability, simplicity, light weight, and freedom from servicing. This paper discusses some of the points to consider in the use of permanent magnets for erase.

If the erasure is to be followed by recording with d-c bias there is no problem. Here the erase should not be designed to demagnetize the tape but to saturate it, and a single saturating magnet is all that is required. However, with this type of recording, a

high noise level is unavoidable and most present day recorders use a-c bias. The following discussion assumes that the erase will be followed by a-c bias recording.

D-C "Pulse" Erasing

With a single permanent magnet of sufficient strength to saturate the tape, the signal may be easily obliterated but the noise level of even a perfect tape




Fig. 1. Curve showing principle of demagnetization by two d-c pulses.

would be fairly high and that of actual tapes is very high. For example, noise levels of 20 to 30 db higher than those normally obtained with a-c erase are common. In addition, the polarized condition of the tape leads to serious even order harmonic distortion in the subsequent recording, a condition which is absent with a good a-c erase. The expedient of a "single pulse" permanent magnet (or d-c) erase can therefore be justified only when cost or simplicity is the prime consideration.

The next step is to consider two d-c "pulses." In principle such a cycle can demagnetize, as shown schematically in Fig. 1. The first pulse should be saturating (in either direction); the second pulse is of opposite polarity and of just such strength as to leave the material with zero magnetization after its removal.

At this point several considerations enter:

1. The hysteresis loop of the material

which we obtain from any gross measurements represents an average over many billions of oxide particles. These particles are crystals or oriented aggregates of crystals, each of which has preferred axes of magnetization. For a given direction of magnetization, each crystal orientation will result in a different contribution to the observed hysteresis loop. Under these conditions, a cycle of two pulses cannot be adjusted to demagnetize all the particles. However, a gross average of zero magnetization can be obtained, and when it is, the noise will be much reduced from that obtained with one pulse because,

- a.) The magnetization of individual particles, while not zero, will likely be less than that resulting from saturation, and
- b.) Noise resulting from tape irregularities of relatively long wave length will be effectively reduced.

2. Any given erase will not be optimum for a variety of tapes, although it may be better than a single-pulse erase for all of them.

3. In actual use, the tape when heard has passed not only the erase head but also the record head. In this process the bias field acts on the tape, even when no audio is recorded. Thus the demagnetization result discussed above is of purely academic interest. What is important is the condition of the tape after erasure and biasing. In biasing, the tape is subjected to an a-c field of increasing and then diminishing strength. For a demagnetized tape the bias (if of good design) changes conditions very little, but for a tape erased by one or a few d-c pulses the change may be considerable. To some extent the bias field acts as an incomplete (i.e., non-saturating) a-c erasure and tends to reduce noise. It may, however, tend to alter an average tape magnetization from the zero value in which a permanent magnet erase cycle left it, and thus tend to increase noise. This will be made clear below.

A characteristic of a tape in which an average zero magnetization has been achieved by a few d-c pulses is that it is composed of a collection of particles all of which may be magnetized. If a small a-c field is applied and gradually reduced to zero, it may demagnetize some of these elements or alter some

*Minnesota Mining and Manufacturing Co., St. Paul, Minnesota.

domain boundaries that are relatively unstable, while not affecting others. When this happens the average magnetization is no longer zero.

Method of Obtaining Data

To take quantitative data, a large solenoid was used to apply known fields to a 1/4-inch square rod, 12 inches long, of oxide dispersion. The magnetization was measured by passing the rod through a pickup coil connected to a ballistic galvanometer. A d-c pulse was administered by setting the desired current from storage batteries in the magnetizing solenoid and passing the rod through the solenoid. Diminishing a.c. fields were obtained in the same way, using a 60 cycle supply with a Variac. The diminishing was done by the movement of the rod rather than by the Variac. After each pulse of d.c., the magnetization of the rod was measured, and after a suitable erase schedule, the rod was subjected to a-c fields and measured after each "shake" beginning with weak and increasing to saturating a-c fields. The units for magnetization were left arbitrary, although they could be converted to absolute values of flux lines or gauss; the field values were measured in oersteds.

The data are summarized in Fig. 2. The schedules of d-c fields used to erase are shown at the left for erasures of from one to five d-c pulses. Beneath each pulse applied is tabulated the residual flux, measured following that pulse. To the right of each schedule is plotted the magnetization as a function of the peak value of the a-c field to which the sample was subjected after erase.

Leaving aside the bottom curve, the curves form a family which illustrate the basic phenomenon. The top curve is a single-pulse d-c erase, which leaves a large magnetization which is hardly reduced by ordinary bias fields (of the order of 200-300 oersteds). The next two curves show two-pulse erasures with obvious improvement over the single-pulse erase. The first of these achieves zero average magnetization after erase, but the a-c field corresponding to the bias increases the magnetization very markedly. The second of these two shows an erase so designed as to leave zero magnetization after biasing with 280 oersteds. Various three, four, and five pulse erasures follow and it may be seen that:

1. Gross, or average, magnetization may be made no more complete but enormously more stable by increasing the number of pulses in the erase schedule.
2. One can alter the shape of the curves deliberately and predictably by choosing the sequence of pulses. As the a-c field is increased following a multi-pulse d-c erase, the material retraces its past history, "forgetting" first the last or weakest d-c pulse, then the

next to last, and so on. This shows the extent to which the erase schedule failed to demagnetize the material and achieved instead merely a zero average flux, as described above.

Experimental D-C Pulse Head

The schedules shown are, of course, not all the data taken. For a given result the magnitude of pulses had to be chosen with great care. In practice, one of the fields from commercial magnets could not be controlled within the fraction of one per cent necessary to get the results shown for a five pulse erasure. A magnetization of 10 to 25 units on the vertical scale of the curves would be a good practical result.

Another factor of great importance in actual tape erasure is that fields applied to the tape are not uniform through the tape. Thus for a given array of magnets the layers of tape next to the magnets might experience fields proportional to but stronger than the fields acting on a more remote layer

of the tape. The last curve of Fig. 2 illustrates the inadequacy of a five-pulse schedule which is similar to the one directly above it but with all values increased by the factor 1.86. It does a poor job, and if one must contend with such variations, either more pulses must be used or poorer results expected.

The schedules shown in Fig. 2 are also non-universal with respect to the magnetic properties of the tape. A schedule best for one tape will not be best for another, although it will be better than a single pulse. Universality is necessarily tied in with a very large number of pulses such as approximate true demagnetization.

In actual tape recording, not only are there gradients in the erasing fields but also in the biasing field. For conventional ring-type record heads, the bias-field gradient across the thickness of the tape may introduce a factor from two to five between the fields near the front and back of the tape. Thus




Fig. 2. Chart showing characteristics of erasure by various schedules of d-c pulses, using rods as the magnetic medium.

committee. They hold 33 minutes of tape at the standard speed of 15 inches.

Three motors are used in the drive system, one a dual-speed synchronous motor to drive the capstan, and the other two on the reel assemblies. All motors are very compact and light in weight, having been especially designed to Ampex specifications. The turntables holding the tape reels are attached directly to the shafts of the rewind and takeup motors. A holddown is used to lock the reels in place. The holddown is constructed in such a manner that it centers and locks the standard NAB reel, as well as the standard RMA reel, without regard to varying thicknesses. Motor shafts 5/16" in diameter allow the use of the smaller RMA reel. Mechanical brakes are employed for providing quick smooth stops at any speed without undue tape tensions and without allowing slack to form at any time.

The drive system was the subject for the most intensive investigation of any part of the machine. Many different types of drives were built up and studied. The various factors which produce speed variations were isolated and analyzed, and methods of construction were devised which eliminated their effect. The result is a remarkably wow-free and flutter-free drive, with a minimum of precise, close-tolerance parts. The fact that speed variations

have been removed by basic design principles rather than by excessive precision in manufacturing has greatly reduced the cost of the drive unit.

Another feature of the drive system is instant starting. When the tape is threaded up, the takeup tension arm is moved into position, which starts the capstan motor. This same arm also automatically stops the machine when the tape runs out or in the event of tape breakage. When the START button is operated, a rubber idler clutches the tape against the capstan and the tape comes up to speed in less than 0.1 seconds. This feature is useful in editing and in cueing programs.

The following pushbutton controls are provided: START, STOP and RECORD. Since these controls are relay operated, they may be governed from a remote location. A selector switch controls the mode of operation, either NORMAL PLAY, REWIND, OR FAST FORWARD. The machine can be readily shifted from one mode of operation to the other, except that in returning to NORMAL PLAY from fast winding, the machine automatically stops to avoid breaking the tape by clutching it into the capstan while moving at high speed. The ability to shift back and forth at will from REWIND to FAST FORWARD assists in editing operations, as the tape can be shuttled back and forth over a given length to determine

the exact location of a particular point in the program.

Head Housing

New heads have been designed which have improved performance characteristics with smaller physical size. Because of the extremely short wavelengths at the high extreme of the audio spectrum at the lower tape speeds, extreme precision in head construction is required to insure interchangeability of recordings on various machines without loss of high frequencies. While a slightly curved gap does not affect the performance of a single machine (the gap effect is readily equalized), such curvature will make it impossible for a group of machines to be aligned so that recordings can be indiscriminately interchanged among them without high-frequency discrepancies. An indication of the accuracy required may be illustrated by the fact that if one edge of the gap is displaced from its proper position by .0003 inches, the response at 15,000 cps will fall off by 2 db. Precision methods of manufacture, combined with the most rigid inspection procedures, assure that the heads will have the required uniformity.

The head housing is a complete plug-in unit containing erase, record and playback heads. Separate record and playback heads retain the valuable feature of allowing direct monitoring

[Continued on page 30]

Fig. 3. Model 300 recorder (left) beside the Model 200, illustrating the reduction in size in the new unit. Also shown is the extended-range speaker system used for critical listening tests. The unique Smith-Selsted tweeter (center) provides flat response up to 20,000 cps.



Problems in Audio Engineering

LEWIS S. GOODFRIEND*

Part IV. A study of sound waves—their characteristics, and their transmission; and an introduction to the wave equation, which governs their propagation.

THIS ARTICLE begins the study of sound waves and their generation and transmission. To establish a starting point we shall define sound and some of its characteristics. According to the "Proposed American Standard Acoustical Terminology," published by the American Standards Association for trial and study, "Sound is an alteration in pressure, stress, particle displacement, particle velocity, etc., which is propagated in an elastic material, or the superposition of such alterations." It may also be defined as "... auditory sensation which is evoked by the alterations described above." Since fundamental laws of physics relate the various types of alterations, one of them—pressure—will be discussed and the material then extended to cover the others. Also, a discussion of the superposition of alterations will be left until later.

If a pressure measuring device is placed in the path of a musical sound wave the oscillogram of *Fig. 1* may be obtained. In order to carry on the analysis of propagation various labels have been placed on the figure and their definitions given below. Those marked with an asterisk are from the proposed American Standard.

Static Pressure*: The static pressure is the pressure that would exist in the medium with no sound waves present. The com-

*Rangertone, Inc., 73 Winthrop St., Newark 4, N. J.

monly used unit is the microbar.

Instantaneous Sound Pressure*: The instantaneous sound pressure at a point is the total instantaneous pressure at the point minus the static pressure. The commonly used unit is the microbar.

Maximum Sound Pressure*: The maximum sound pressure for any given cycle of a periodic wave is the maximum absolute value of the instantaneous sound pressure occurring during that cycle. The commonly used unit is the microbar.

Note: in the case of a sinusoidal sound wave this maximum sound pressure is also called the pressure amplitude.

Peak Sound Pressure*: The peak sound pressure for any specified time interval is the maximum absolute value of the instantaneous sound pressure in that interval. The commonly used unit is the microbar. **Note:** in the case of a periodic wave, if the time interval considered is a complete period the peak sound pressure becomes identical with the maximum sound pressure.

Effective Sound Pressure* (Root-Mean-Square Sound Pressure): The effective sound pressure at a point is the root-mean-square value of the instantaneous sound pressures over a time interval at the point under consideration. In the case of periodic sound pressures, the interval must be an integral number of periods or an interval which is long compared to the period. In the case of nonperiodic sound pressures, the interval should be long enough to make the value obtained essentially independent of small changes in the length of the interval. **Note:** the term "effective sound pressure" is frequently shortened to "sound pressure."

Periodic Wave: A periodic wave is one in which the values of the pressure amplitude recur for equal increments of time or distance, as shown in *Fig. 1*.

Fundamental Frequency*: The fundamental frequency of a periodic quantity is the frequency of a sinusoidal quantity which has the same period as the periodic quantity. The fundamental frequency of a periodic quantity is also the reciprocal of the period.

Period: The period of a periodic quantity is the smallest value of the increment of the independent variable for which the function repeats itself.

Wavelength*: The wavelength of a periodic wave in an isotropic medium is the perpendicular distance between two wavefronts in which the displacements have a phase difference of one complete period.

Figure 2 shows a circular piston having a plane face, moving in a cylindrical tube. The far end of the tube may for the moment be considered to be completely sound absorbent. This will eliminate any necessity to consider reflections. As the piston moves to the right it compresses air immediately in front of it. This small element of air then compresses the air to its right, thereby sending the compression down the tube. If the displacement of the piston takes place in a short time a steep front pulse will be sent down the tube. A picture of the pulse at successive intervals of time is shown in *Fig. 3*.

If the piston is moved to the left the air immediately in front of it will be





Fig. 1. Oscillogram of a sound wave.

P_a = absolute sound pressure measured above zero
 P_s = static sound pressure
 p = instantaneous sound pressure
 P_m = maximum sound pressure λ = wavelength
 T = period ξ = displacement

Fig. 2. Pressure and rarefaction waves in tube excited by piston with plane surface.

Fig. 4. Instantaneous pressure along tube as result of oscillating (sinusoidal) motion of piston of Fig. 2.






Fig. 3. Movement of pressure wave down tube of Fig. 2.

rarefied and a rarefaction wave will be sent down the tube.

If the piston is driven by a mechanism which will impart to it a sinusoidal motion the pressure in the tube after a short time will vary sinusoidally with distance, as shown in Fig. 4, as a train of waves is sent down the tube. Since the waves are being generated by a plane surface, it may be seen that the pressure in any one plane parallel to the piston face, neglecting the frictional drag near the surface of the tube, will be equal, so that the waves are said to be plane waves.

Plane waves and the theory of their propagation offer an excellent means of analyzing many audio problems. They permit simple studies of loudspeakers, the transmission of sound

through panels, sound at long distances from the source, and sound in bars and rods.

As an example of plane waves in bars consider what happens when a steel bar is struck on the end with a hammer. When a thin circular plate is struck in the center, waves similar to those in the tube are sent out through the plate in all directions, but they are restricted to the plate. This is a case of a two-dimensional wave and is illustrated in Fig. 5. When a source of sound radiates in all directions, three dimensional or spherical waves exist as is shown in Fig. 6, and in the simplest form would consist of a small hollow, spherical ball fed with air through a small tube. As the sphere gets larger and smaller it




Fig. 7. Elements of pressure waves in (A) two-dimensional plane, and in (B) three-dimensional space.

successively compresses and rarefies the air. If we place a loudspeaker on the outside wall of a building and measure its radiation pattern we can see that it will generate spherical waves over a hemisphere.

The extension of plane wave theory to both the spherical and two-dimensional cases simplifies many problems and greatly reduces the mathematical work involved. If we examine portions of the spherical wave and two-dimensional wave at long distances from the source as shown in Fig. 7, we see that a small element of either is very much the same as an element of the plane wave, and it is possible to prove this extension mathematically.

Some of the properties which we would like to know about sound waves are: velocity through the medium, velocity of the particles of the medium, particle amplitude, pressure (rms or peak), energy, and intensity. From the physical and thermodynamical principles of continuity, adiabatic expansion and compression gases, and the equation of motion, it is possible to derive an expression relating the particle characteristic under study (displacement, pressure, etc.) to the distance the wave travels down the tube and to time. This equation is the so-called wave equation, and for pressure in

plane waves the form

$$\frac{\partial^2 p}{\partial t^2} = \sqrt{\frac{\gamma p_s}{\rho_s}} \frac{\partial^2 p}{\partial x^2}$$

The constant term, which we may call c , may be shown to be the velocity with which the wave travels down the tube. It is also the velocity of waves propagated in either two or three dimensions. In the wave equation the symbols are as follows:

- P_s = Static pressure in dynes per square centimeter
- ρ_s = Static density of the medium in grams per cm³.
- γ = the ratio of the specific heats of the gas (1.4 for air at room temperature)

Assuming that the displacement ξ varies sinusoidally according to $\xi = a \sin(\omega t - 2\pi x/\lambda)$, a generalized form for sinusoidal motion, the particle velocity u may be obtained from the above expression giving

$$u = \omega a \cos(\omega t - 2\pi x/\lambda) \text{ cm. per sec.,}$$

with the maximum particle velocity $u_m = \omega a$ cm. per sec. The maximum particle amplitude is $\xi_m = a$ cm.

The instantaneous pressure in the wave can be determined from the other quantities giving

$$p = p_s \gamma k a (\cos \omega t - k x) \text{ dynes per cm}^2, \text{ where } k = 2\pi/\lambda.$$

Determining the energy density (energy per unit volume) in the wave involves the use of calculus, but when the operation is performed we obtain the following expression:

$$E = \rho_s u_m^2/2 \text{ ergs per cm}^3.$$

If we rearrange some of the terms and make the correct substitutions it is possible to obtain the energy equation in another form, $E = \rho_s u^2$ ergs per cm³. The total energy in a given volume may, of course, be obtained by multiplying the energy density by the volume.

Finally, the intensity of the sound is obtained by multiplying the energy

[Continued on page 31]



Fig. 5. Showing pressure and rarefaction in two-dimensional sound wave.




Fig. 6. Pressure and rarefaction existing in a three-dimensional sound wave.

TABLE I

1 microbar	= 1 dyne per cm ² .
1 dyne per cm ² .	= 1.45×10^{-5} lbs./in ² .
1 erg	= 1 dyne-centimeter
	= 7.38×10^{-8} ft. lbs.
1 erg per sec.	= 1×10^{-7} watts
1 erg/sec./cm ² .	= 1×10^{-7} watts/cm ² .

TABLE II

For air at 20° C. and 760 mm. pressure	
P_s	= 1.013×10^6 dynes per cm ² .
ρ_s	= 1.21×10^{-3} grams per cm ³ .
γ	= 1.40 (dimensionless)
c	= 34,300 cm. per sec.

RECORD REVUE

SOME MONTHS BACK I went over the LP record as it then appeared to me, while waiting for the 45-rpm RCA record to take its place beside it. Finally, months later, my RCA player has arrived and is in full use and—perhaps a bit late and anticlimactically—I'm in a position to make similar remarks on the second type of record. My player, incidentally, has been encased by RCA in a superb brass-bound mahogany box, affectionately dubbed the "Humidor" by all concerned; its vital parts however include a diamond point GE cartridge which allows me to make far more accurate comparisons than would the standard crystal cartridge, since I can play all types of records through a single preamplifier and thus pin down a number of factors, in order to judge variations in recording curves, etc. as the ear hears them. (RCA also provides its own preamplifier which I will use alternatively in order to get the "official" equalization as chosen by the company itself. This unit is actually two preamplifiers, one being for the low-level 45-rpm records and the other, apparently, for playing standard records via magnetic pick-up.)

If it were a question of black and white (as it must be for some people) I would choose LP over RCA 45 without hesitation, for the *classical* field of music, on numerous counts. But it is far from a black and white matter, and in any case, every so often us classical guys must admit we're only a backwater in the business, even if an important one. I can see where most people who habitually play single records, of which there are millions (both records and people) would find the unlimited choice of program offered by the RCA changer system decidedly preferable to the fixed-choice necessary with the long playing record. Nor are all single records popular, by any means. Huge

*279 W. 4th St., New York 14, N.Y.

This page should be printed in delicate pink this month, reflecting this department's slight embarrassment at a colossal injury done to a gentleman named Koeschel—not Koeschel, as one of our knowing readers pointed out to me! (You'd be surprised at the readers this magazine has acquired in the non-audio fields. We have to watch our P's and Q's hereabouts.) My only defense, such as it is, comes in the accepted fact that *most* German names that involve *sch* sounds use the *sch* spelling and I took same for granted. Maybe it was that the usual form is just plain "K.", which dodges the issue. (See AUDIO ENGINEERING for June—also once in the July issue; too late to catch it.)

EDWARD TATNALL CANBY*

numbers of singles in the classical field, notably in opera and in celebrity recordings, are sold every year. This is a genuine point in favor of the 45-rpm short record which nobody will deny.

As for the rest of classical music, it is clear to me that if LP had never been heard of, the new 45 system would represent a clear improvement in many respects within the established system of 4-minute recordings. The records are cheaper, unbreakable, enormously more economical of space, and so on. Who could deny this? The disadvantages of the 45 records are mostly of a sort that, like similar troubles with LP, can be remedied in time. The system itself, including the simplified center operating change mechanism, is basically sound—again as a variation upon the systems already in use for 78-rpm records. The idea of LP aside, granting that one is to stick to the standard-length record time (and that is the basic decision) I can't think of any aspect of the 45-rpm system that can be seriously criticized in principle. Even the speed—once more, granting the same premise, that standard-length records are to remain, is not unreasonable and can, I'd say, be fairly cited by Victor as an excellent, if not the best speed—all factors considered—for this playing time. The advantages of the 45 speed over the 33 in the case of the 7-inch record are fairly clear when the Columbia small record is stacked up against the RCA. The Columbia, as far as I can see, wastes space and even so comes pretty close to the center for the slower speed. It would seem that as both size of record and rotational speed are reduced, the various factors do in fact tend to converge upon one speed as optimum. It might have been 50 or 55, with another record size, but, *given these conditions excluding any other than standard playing time*, 33 would most likely be too slow. External reasons, such as the prevalence of 33 in existing equipment, would have to be applied to justify that speed for any standard length record and here RCA would surely be right in saying that this is an attempt to establish a new home standard, optimum for the conditions. Why use a professional speed which is both irrelevant and unsuitable?

Here, then, is the point that most needs clarifying—before any question of practical operation of the new records and equipment is even raised. The basic question was from the beginning—shall we stick to standard playing length, and thus be able to duplicate all existing and forthcoming recordings

in the 78-rpm form and on the new form? Or shall we give up this uniformity and produce some other length of play, necessitating two entirely different forms of release for each recording, plus the patching together of all present recordings, or alternatively, the breaking up of longer ones to fit the 78-rpm length? On this question primarily the break occurred not on details, not even on which technical system is potentially better audio—the subject of an enormous amount of engineering talk these last months!

For, once the basic break has been made, once the standard record length has been given up—then the Columbia line of argument comes into force: given *this* condition, what combination of factors works out best—what record size, what length of play, what speed? Given *this* condition—the 78-rpm length of play entirely abandoned, then the 12-inch and 10-inch records at 33 become quite reasonable. Again, perhaps other sizes and other speeds might have been possible, but if one gives up the standard play length, the new length must be significantly longer or the change is utterly pointless; significantly longer means a lot more than even double-play. To succeed, one must, in this case, go the whole hog, and the whole hog appeared to be the present LP, which has abundantly justified its daring, whereas a shorter long-play record, however fine in quality, might have fallen horribly.

I harp on this because it seems to me that minor technical differences and troubles have taken up too much of our thinking these days; most of them are possible to cope with within the two existing systems; it is the basic systems themselves, as conflicting principles, that count most. However, let me enumerate some RCA-Victor characteristics as presently showing themselves to me in the actual playing.

My impression is that the RCA recordings on 45 are considerably less, shall I say, *temperamental* than the LP recordings. The LP's vary greatly in many respects not only in plain good and bad but in *apparent* recording characteristic, to be compensated for by ear-controlled equalization, and other technical matters. There are a good many inherent wobbles in some spots on the LP's, and various minor imperfections such as "ghosts" (echoes) in adjacent grooves, occasional over-cut passages that on some equipment do not track, and so on. The 45's seem to me inherently more stable and, with the faster speed, this would seem reasonable. The degree of apparent distortion, too, seems to vary greatly from LP to LP—though I know enough by now to suspect equipment no matter how expensive, first, the record last. (I try LP's on several quite different types of playing equipment for this reason. (It is perhaps beyond my

[Continued on page 34]



Audio Engineering Society,
Box F, Oceanside, N. Y.

The Journal of the AUDIO engineering society

Containing the Activities and Papers of the Society, and published monthly as a part of AUDIO ENGINEERING Magazine

OFFICERS

C. J. LeBel, President

C. A. Rackey.....Executive Vice-Pres. John T. Mullin.....Western Vice-Pres.
Norman C. Pickering.....Secretary Ralph A. Schiegel.....Treasurer



Message from the President

For some time the need for a professional society devoted exclusively to audio engineering has been evident. By the beginning of 1948 opinion had become so unanimous in this respect that it became possible to form such a society. In the short time which has passed since then, the Audio Engineering Society has succeeded in accomplishing many things.

Monthly meetings are held regularly by a number of local sections, with papers being read which pertain to specific phases of the audio engineering art. In New York this spring, a series of lectures on "Elements and Practices of Audio Engineering" met with marked success, and other sections are planning to repeat it. A similar series on all phases of recording and reproduction is now being announced for this fall. During October, in conjunction with our first annual convention, The Audio Fair will be held in New York with exhibits and papers marking the activities.

With this issue of AUDIO ENGINEERING magazine, the Journal of the Audio Engineering Society makes its bow, marking one more progressive step taken by the Society.

As president of the Society, I look forward to increased activity in the coming months and years as the field of audio engineering attains the independent recognition which is justly its due.

C. J. LeBel

Coming to the Audio Fair?

Providing for the first time a suitable exhibition medium for the demonstration of audio equipment, The Audio Fair which opens at the Hotel New Yorker on October 27 will give audio engineers an opportunity of both seeing and hearing the new equipment which will be presented on the exhibit floor. Coupled with the first convention of the Society, together with important papers and the installation of officers for the following year, The Audio Fair merits the interest of all.

MANY PROMINENT MANUFACTURERS of audio equipment are, and will be there to reveal their latest developments and to demonstrate their equipment. The Audio Fair—the first exhibit ever held exclusively for the audio industry—will be held in conjunction with the annual meeting and convention of the Audio Engineering Society at Hotel New Yorker in New York City on October 27, 28, and 29, 1949.

The entire sixth floor of the hotel has been reserved for the exhibits, guaranteeing each exhibitor and those in attendance an opportunity to see and hear the new products with a minimum of interference. Some of the nation's leading commercial organizations have already indicated their intention to display their products.

In connection with the exhibit, the Society will hold technical sessions on each day of the meeting, with many significant papers already scheduled for presentation. In addition, a banquet will be held on the evening of October 27. No registration fee will be charged to anyone wishing to attend the exhibits, nor to members for admittance to the technical sessions. Non-members may attend the papers sessions on payment of a small registration fee.

Several unusual projects are being prepared for the Audio Fair—projects which will hold a high degree of interest for those whose primary interest is in the field of audio engineering. As these plans reach maturity, they will

be announced in detail in this space. Already slated for an important part at the meeting is the subject of recording—disc, film, and magnetic. High-fidelity sound reproduction and public address equipment will also be demonstrated and discussed.

Mark down the time and place to meet other members of the Society for an absorbing insight into the latest developments in the field of audio engineering—plan now to attend The Audio Fair on October 27, 28, and 29 at Hotel New Yorker, in New York City.

Employment Service

Starting with the September issue, The Journal is inaugurating a free employment service for members and for industry. The service will consist of listing brief announcements of available personnel and positions. If you are either a member of the A.E.S. seeking employment or an employer looking for an audio engineer, The Journal will print, free of charge, a brief announcement describing yourself or the position. Anonymity will be preserved by the use of box numbers for reply. To avoid errors due to rewriting, please compose these notices carefully and keep them brief. Notices for the next issue must be in before August 10. Send them to AUDIO ENGINEERING Magazine, Attention AES Editor, 342 Madison Avenue, New York 17, N. Y.



A New Electronic Audio Sweep-Frequency Generator

By H. TOOMIN*

Optimum presentation of frequency-response data on a 'scope screen requires a special form of a-f signal generator. Circuit details of such an instrument are outlined by the author.

AN AUDIO SWEEP FREQUENCY GENERATOR is an instrument designed primarily to make possible the presentation of audio frequency response curves on a cathode ray oscilloscope. Several approaches to this problem have been made in the past^{1,2,3} with results excellent in the high-frequency register but which have left much to be desired in the presentation of the bass response. Figure 1 shows a typical trace for a flat system using a commercial sweep generator. It is apparent that even though the system measured is flat to below 40 cps, there is very little informa-

tion presented for frequencies below 500 cps. The most obvious fault with the presentation of Fig. 1 is the spacing of the cycles. The spot moves at a uniform rate across the screen so that just as much time is spent in

traveling from 40 to 50 cps as is spent between 4000 and 5000 cps. Consequently, comparatively few cycles appear in the initial portion of the oscillogram. The wavelength or the distance between cycle crests is approxi-




Fig. 1. Photo-electric-Scanner type audio sweep generator signal presentation.

*11 Bayless Ave., Binghamton, N. Y.

¹ Electronic-Type Oscillographic Frequency Response Curve Apparatus of Wide Application, W. G. Gordon and A. H. Mutton, *J. Instn. Engrs. Australia*, Feb. 1937

² Automatic Recording of Audio Frequency Characteristics, *Radio Engineering*, Feb. 1937

³ Audio Frequency Response Curve Tracer, J. B. Sherman, *Proc. I.R.E.*, June 1938




Fig. 2 (left). Output presentation of constant wavelength generator. Note evenly distributed cycle peaks. Level is constant within $\frac{1}{2}$ db from 20 cps to 20 kc. Fig. 3 (right). Oscillogram of 20 to 20,000 cps frequency response of UTC Model 3AX Line Equalizer shown in log-log coordinates. The points of maximum equalization were set for 10 db at 100 cps and at 6000 kc.




Fig. 4 (left). Low-pass single-section RC network shown in log-log coordinates from 20 to 20,000 cps. $RwC = 1$ at 250 cps and at 6000 cps. Fig. 5 (right). High-pass single-section RC network shown in log-log coordinates from 20 to 20,000 cps. $RwC = 1$ at 8 kc. Note linear 6 db per octave rise.

mately inversely proportional to the log of frequency. It can be readily seen that a much better presentation would result if the wavelength were constant and independent of frequency. Figure 2 illustrates this point with an oscillogram taken with the new generator here to be described. The sweep band from 20 to 20,000 cps is shown. Note that the wavelength is approximately constant from 20 to 2000 cps. This feature makes possible the presentation of frequency response

curves showing smooth contours in the bass as well as in other regions of the audio spectrum. Figures 3, 4, 5, and 6 illustrate various response curves obtained with this new generator.

It is highly desirable to have the frequency response curves plotted in Log vs Log coordinates so that they will closely resemble curves plotted in the conventional manner. That is, the vertical scale should be linear in decibels and the horizontal scale should be linear in log of frequency. Since

an oscilloscope responds linearly to equal voltage increments and we wish it to respond linearly to equal decibel increments it is necessary to distort the signal applied to the vertical amplifier so that its peak value is always proportional to the logarithm of the output signal from the equipment being tested.

Generator Design Problems

The design of a suitable audio sweep-frequency generator consists of several problems. Since the constant-wavelength feature depends on maintaining the proper sweep velocity at each frequency on the scale, a suitable sweep-wave shape must be defined and then generated. The frequency must be made to change in synchronism with the sweep voltage and in the proper increments to maintain a logarithmic frequency-scale distribution. Methods for controlling low- and high-frequency band limits must be provided to prevent instability and frequency drift. Frequency markers are necessary for checking the frequency scale. A logarithmic distorting am-




Fig. 6. 50-cps calibration null. Note smooth contours below 100 cps, and sharply defined null.

plifier must be designed for converting the vertical scale to decibels. Each of these problems will be discussed.

It has been seen that the constant-wavelength feature has worthwhile advantages. The following discussion will develop the expression for the sweep

direction. A plot of this horizontal deflection as a function of time is shown in Fig. 8. On the right edge of this plot is shown a scale of frequencies from which the frequency at any instant can be determined. It will be observed that for 90 per cent of

the sweep period the frequency is below 200 cps with the change from 200 to 20,000 cps occurring in the last 10 per cent of the time. It thus becomes evident that a major portion of the sweep time must be spent in the bass register to allow a large number of cycles to occur so that the curves drawn will be smooth in the bass region.

Sweep Circuit Details

Needless to say, the electronic circuit that fulfills these conditions did not evolve over night but required trials of many possible combinations before a completely satisfactory system was devised. Figure 9 shows the principles of the final circuit, some details being omitted for the sake of clarity. A linear sawtooth wave, generated by the 884 thyatron, is converted to the required wave shape and then drives a remote cutoff reactance tube to frequency modulate one oscillator of a B.F.O. The linear sawtooth wave, $e = at$, is distorted to a




Fig. 7A (left) and 7B (right). Curves of Equations (1) and (2) showing conditions imposed on sweep velocity and frequency-scale division.

wave shape that makes possible this type of presentation. In the case of a wave drawn by a spot moving across an oscilloscope screen while the frequency of vertical motion increases as the spot progresses, a constant wavelength will be maintained only if the horizontal component of the spot velocity increases in proportion to the increase in frequency. This can be stated mathematically as follows:

$$f\lambda = v \quad (1)$$

where f is the frequency at any point on the horizontal scale, λ is a constant wavelength, and v is the instantaneous horizontal spot velocity at the point. Equation (1) is illustrated in the plot of Fig. 7A.

The condition of logarithmic horizontal scale distribution can be stated as follows:

$$s = k \log f/f_0 \quad (2)$$

where f_0 is the initial frequency at the left edge of the screen and s is the distance from f_0 to f . k is a constant dependent on total scale length. Equation (2) is illustrated in the plot of Fig. 7B.

Equations (1) and (2) can be solved simultaneously to obtain the equation of s as a function of time, since v in equation (1) is equal to ds/dt . The resulting equation for a 5-inch scale, 20 to 20,000 cps bands limits is:

$$s = 0.724 \log_e 1 - \left(\frac{1}{.00999t} \right) \quad (3)$$

where t is expressed in per cent of a sweep period. This expression defines the manner in which the spot must traverse the screen in the horizontal




Fig. 8. Required sweep-wave shape plotted in inches horizontal deflection vs. per cent of a sweep period. Frequency scale on right shows required position of each frequency for logarithmic scale.




Fig. 9. Simplified circuit diagram of sweep generator, showing wave form at significant points in the circuit.




Fig. 10. Oscillogram comparing calculated sweep wave shape with experimentally obtained output from generator of Fig. 9.

log function by means of 1N34 germanium crystals which have the characteristic that the voltage across the contacts is proportional to the logarithm of the current through them⁴. In this case a constant current from the B supply passes through the contact rectifiers from which is subtracted the amplified saw tooth wave at the output of the second stage. The wave form at the input to the third stage can therefore be expressed as follows:

$$E' = c \log_e (I_B - I_{saw}) \quad (4)$$

Where E' is the voltage across the contact rectifiers and c is a constant of proportionality.

The wave form at this point must be inverted to obtain the required sweep voltage since the inversion puts a minus sign before the expression of equation (4) and

$$-\log_e (I_B - I_{saw}) = \log_e 1 / (I_B - I_{saw})$$

The output of the amplifier stage, E'' , is therefore of the required wave form since I_{saw} is proportional to time and I_B is constant. Thus:


$$E'' = c \log_e 1(b - a't)$$

where c' , b , and a' are constants. See Fig. 9.

Fig. 10 shows an oscilloscope in which E'' is plotted against time and is superimposed on a drawing of the calculated curve. The close agreement between the experimentally generated curve and the theoretical curve is readily apparent.

It will be observed that this wave-shape requires great accuracy and stability of the trigger point since approximately half the screen is covered in the last 1 per cent of the sweep period and a very slight jitter in trigger time could easily cause the upper band limit to vary between 20 and 50 or more kc. Stability of the upper band limit is a problem that was solved by causing the trigger time to be determined by the output frequency. Note in Fig. 9

Fig. 11. Circuit of logarithmic distorting amplifier for obtaining vertical deflection linear in decibels.



that the LC network, tuned to 20 kc, in the grid circuit of the 884 is excited in a constant-current fashion from the audio output of the generator. The voltage across this circuit therefore rises as the output frequency approaches 20 kc and triggers the sweep when it is large enough to overcome the bias on the grid of the gas tube. Thus the trigger occurs at the same frequency for each sweep regard-

less of the total time taken by individual sweep periods. Since the a.c. grid voltage on the 884 increases as the output frequency approaches 20 kc, and ends the sweep when it is large enough to overcome the bias, controlling the bias offers a means of varying the upper band limit. A reduction in bias will lower the voltage required to trigger the sweep and will therefore lower the upper band limit. This control appears on the front panel as the upper band limit control. The upper limit may be set anywhere between 2000 and 20,000 cps.

Control of the lower band limit is

achieved by setting the initial bias on the reactance tube grid, thus changing the initial frequency without disturbing the horizontal scale distribution. A decrease in bias merely cuts off the low end of the sweep range and thus raises the lower band limit. A study of the equations reveals that this method of control does not change the constant-wavelength feature except to

[Continued on page 28]





Fig. 12. Input voltage versus output decibels curve for amplifier of Fig. 11 showing linearity of vertical decibel scale.

⁴Audio Frequency Response Curve Tracer, J. H. Jupe, *Telephony*, Aug. 16, 1947

FONO-FITTED



CARTRIDGES



... you draw the curve
WE'LL BUILD THE CARTRIDGE

Your specifications . . . your special requirements in phono pickup cartridges . . . are ideally "custom-solved" through E-V creative engineering . . . unusual manufacturing facilities . . . and inherent advantages of exclusive TORQUE DRIVE.*

CUSTOM RESPONSE

Smooth upper response with roll off frequency to your specifications or wide range, peak-free response to 10 kc. You draw the curve, we'll build the cartridge.

VOLTAGE

E-V TORQUE DRIVE cartridges provide the highest compliance per volt output. For example, the E-V 14 cartridge tracks at 5 grams with excellent wave form down through 50 c.p.s. on the RCA 12-5-31V record at 1 volt at 1,000 c.p.s.

TRACKING FORCE

With the high compliance and low mass of the driving system, needle forces at 5 grams for both one and three mil records are used in everyday production by leading manufacturers. Cartridges with even lower needle force with slight reduction in voltage are thoroughly practical. 3 gram tracking pressures are definitely in sight.

COMBINATION One and Three Mil

E-V TORQUE DRIVE again leads in twin needle cartridge design. Tracking force of 5 grams on both one and three mil records precludes weight changing. Straight line needle position assures accurate set down when used with changers. Approximately the same output is obtained on both stylus. The E-V Twin-Tilt cartridge mounts in any arm with 1/2" mounting holes with no modification except adjustment for correct needle force.

MOISTURE PROOFING

The cartridge is entirely filled with DC4 Silicone jelly—the material that is used for inhibiting moisture on aircraft wiring. Tests indicate that it increases the life of an ordinary crystal some 20 times. This is a plus feature, found in all E-V crystal cartridges.

Our engineering staff and full facilities are at your service. Contact us today.



Modern One-Acre Plant with Complete Internal Facilities for Quality-Controlled Volume Production

From original conception to final product, you get full benefit of the unusual E-V processes. Here are E-V laboratories, where constant research keeps making new contributions to the Art. Here we make tools and dies . . . die cast, plate, screw machine, stamp, mold plastics, and assemble. Here we use specially designed test equipment for quality control. With all these facilities, we produce high standard acoustical products in quantity, with utmost economy. Come—see this plant in action.

NO FINER CHOICE THAN

Electro-Voice

*E-V Pat. Pending
Licensed under Brush patents

Export: 13 East 40th St., New York 16, U.S.A.
Cables: Arlab


AUDIO ENGINEERING ● AUGUST, 1949

ELECTRO-VOICE, INC. • BUCHANAN, MICHIGAN

27

HARVEY

takes great pleasure in presenting the **NEW**
MAGNECORDER PT6-JA



PT6-JA recording mechanism and amplifier


MAGNETIC TAPE RECORDER

The two-case portable Magne recorder PT6-JA is designed for the professional user. Conforms to all N.A.B. specifications. Frequency response 50 to 15,000 cycles—2db, less than 2% harmonic distortion. Two tape speeds, 7 1/2" and 15" and high speed rewind (time 45 sec.) 10-watt audio amplifier external speaker. VU meter built-in. **\$499.50**

Same as above but with high-speed forward **\$515.50**

AND THE NEW DUOTAPE MAGNETIC RECORDER

PARTS KIT



Anyone can assemble this kit with screwdriver, pliers and soldering iron. Precision engineered parts, panels drilled, difficult assemblies factory assembled and tested. Contains motor, all tape parts, erase/re-record/reproduce head, oscillator coil, hardware and full instructions. Amplifier

circuit and parts list included. Playing time one hour on dual tape, records half hour in each direction. Recording speed 7 1/2", response excellent from 80 to 9000 cycles. Complete kit of parts **\$44.95**

Telephone: **2-1500** LUXEMBURG

HARVEY
RADIO COMPANY INC.

103 West 43rd St., New York 18, N. Y.

For FREE Literature, write Dept. A.
COME IN FOR DEMONSTRATION

IN STOCK FOR
IMMEDIATE DELIVERY

really excellent a-c erase, although it may be only slightly poorer than a typical cheap a-c erase and bias system in which there may be bad wave form and/or d-c components. D-c erasure is, therefore, not to be considered for machines in which maximum quality is necessary; for the cases where it is to be used, the information given above may be of value in design and testing.

The author wishes to thank the management of the Minnesota Mining and Manufacturing Company for permission to publish the data contained in this paper, which was obtained in connection with research on "Scotch" Sound Recording Tape.

MAGNETIC RECORDER

[from page 18]

from the tape. Opening the gate of the head housing removes the tape from contact with the heads for fast winding. Threading is extremely simple, as the tape can be merely dropped between the open gate and housing with no fear of snarling or catching. Tilt adjustments are provided on the record and playback heads so that they may be aligned while the machine is running.

Amplifier Assembly

A great deal of work has gone into the simplification of all electronic components to reduce size and cost. Wherever possible, costly transformers have been eliminated, and dual tubes such as the 6SN7 have been used to reduce space requirements.

The recording amplifier has a bridging-input transformer, which can be used either matching or bridging, and the amplifier has sufficient gain to record from any line level from —30 VU up. Ample recording current is provided so that no distortion is introduced by the recording amplifier well beyond the current necessary to saturate the tape. A screwdriver gain control is provided, as well as a high-frequency equalizing adjustment and a bias current adjustment.

A novel bias and erase supply has been provided which leaves the tape remarkably quiet, and which is uncritical to voltage variations and other adjustments.

The playback amplifier will deliver + 25 dbm at 1 per cent total harmonic distortion into a 150- or 600-ohm line. This is ample reserve for the normal operating level of + 4 VU to + 8 VU. A screwdriver gain control is provided, and a high-frequency equalizing adjustment for flat playback response from a standard tape.

Overall performance characteristics are well within the proposed NAB

SIMPLEX RECORDER TAPE SPLICER

(Pat. Pending)

A MUST FOR EVERY TAPE USER!!
NOW EDIT & SPLICE ALL TAPES IN SECONDS
Reclaim and use all odd lengths of tape

- NON-MAGNETIC BLOCK
- PRECISION MACHINED
- JOINT STRONGER THAN TAPE
- EVERY SPLICE STRAIGHT & TRUE
- EVERY SPLICE MADE AT CORRECT ANGLE

When Ordering Include Amount for Splicing Tape

Dealer Inquiries Invited
Manufactured by

BURNETT SERVICE CO.

178 West 168th Street

New York 52, N. Y.



Price **\$5.95**

Less Splicing Tape

Uses Standard Scotch
Splicing Tape No. 41
76c per 66 ft. roll
EVERYWHERE

standards. Frequency response is ± 2 db from 50 to 15,000 cps at 15 inches per second, and ± 2 db from 50 to 7500 cps at 7.5 inches per second. The signal-to-noise ratio is better than 60 db measured in accordance with the NAB definition (ratio of peak recording level to total unweighted noise level recording zero signal; peak recording level is that point at which the overall total harmonic distortion does not exceed 3 per cent measured on a 400 cps tone).

At the 15-inch speed, flutter and wow are well below 0.1 per cent. This measurement is made on a bridge which measures all flutter components from zero to 300 cycles, using a signal of 3000 cycles. At 7.5 inches, the flutter and wow are less than 0.2 per cent.



The final test of performance is in listening. The most critical test that can be made is the "A-B" test, whereby the output of the recorder is compared with the input by rapidly switching the monitoring equipment between input and output. Because of the minutely detailed comparison which can be made at the time of switchover, slight discrepancies between two systems can be detected by means of the A-B test which would never be noticed if the systems were listened to separately. When making critical A-B tests on the Model 300, using live program material of the most exacting nature, and with the highest quality amplifier and speaker systems, it is impossible to distinguish recorded material from the live program.

PROBLEMS IN AUDIO

[from page 20]

by the velocity of the sound. This gives the expression $I = c E$ or $2\pi^2 \rho_s^2 c^3 a^2 / \lambda^2$ or $I = 2\pi^2 \rho_s^2 c f^2 a^2$ ergs/sec/cm².

In all of the above equations the units have been given in the metric system, which is the standard system of units. However, since many authors still use other systems, Table I gives the relation of metric units to the others, and Table II lists the reference values of physical constants. It is important to remember that the constants of the medium change with temperature and it is therefore necessary to use the appropriate values for the temperature at which the computation is to be made. The values given here are for room temperature, 20° C. being equal to 68° F., which is close to the normal working temperature of most places in which audio work is carried out and for which calculations are of importance. In the following articles, consideration will be given to generators and sources, and to applications of the material in this article.



New Yeoman Transformer Series



**Provides Famous
ADC Quality
at Low Cost**

The unvarying high quality of ADC transformers has been recognized by electronics engineers through the years. This record for dependability and close tolerances over wide frequency ranges results from:

- Training and experience in transformer design.
- A careful system of production testing.
- Modern production methods.
- Use of only quality materials.


NOW! ADC has designed a new line of transformers to meet a present day industry need for high transformer quality at lower prices.

Yeoman Series for Quality at Lower Price


The Yeoman series of low-priced transformers includes a number of new designs not previously offered by ADC, and some features of both the famous ADC Quality Plus and Industrial lines. Substitution of open frame construction for hermetic seals and flexible leads for solder terminals are among design changes made in the interest of economy.

The industry will find many uses for the accurate, dependable, trouble free performance of ADC transformers in the Yeoman price range. This new transformer line covers all types of applications; i.e., input, output, bridging, power transformers and chokes.

For full information about ADC transformers,
Write Today for your new ADC catalog.



Industrial Series



Quality Plus Series



Audio DEVELOPMENT CO.

"Audio Develops the Finest"

2851 13th Ave. South, Minneapolis 7, Minn.

Audax
Trade Mark

reproducers



for
Microgroove DISCS
Standard DISCS
Vertical DISCS

**The Standard by Which
Others Are Judged
and Valued**

It is futile to buy the most modern records, if you do not give them the very BEST pick-up to bring out their built-in excellence!

There is so much in present-day discs, that even a mediocre pick-up is bound to bring something out of them. However, to obtain the fullest results of which these discs are capable, they must be reproduced with the finest reproducer for that purpose—the AUDAX.

Remember, two singers may both be able to hit "high C" . . . yet one will please the ear—the other not at all. There is much more than mere WIDE-RANGE to quality reproduction. AUDAX reproducers deliver not merely WIDE-RANGE, but also all vital factors essential to highest quality of musical performance and unequalled

EAR-ACCEPTABILITY

*Write for complimentary pamphlet on
life of permanent points*

AUDAX COMPANY
500 Fifth Avenue
New York 18, N. Y.

*"Creators of Fine Electronic-
Acoustical Apparatus since 1915"*


Techni - Briefs

TUBELESS "HI-FI" TUNER

High-fidelity addicts will remember the Western Electric 10A Radio Receiver as, for its time, one of the best from the standpoint of quality but it was not commercially available to the

is available—consisting of the coils, tuning capacitor, slide-rule dial, and chassis—it is possible to assemble the tuner with any desired chassis and capacitor, provided it covers the tuning

Fig. 1.



home user. The circuit of this tuner was simplified and appeared on the market as a wide range unit, employing a four-gang capacitor and a total of eight coils (two of them untuned) and three or four tubes. Having a wide pass band, it was useful only in close proximity to radio stations, and the sensitivity was not very great for this reason. However, the audio quality was excellent, and there are many of these wide-range tuners still in use.

Utilizing the same circuit principles, a new tuner has recently appeared which serves practically the same purpose. It is broad, and thus suffers from no side-band cutting; it has low sensitivity, which is desirable for tuners of this type; and it has remarkable audio quality. The circuit of the tuner is shown in Fig. 1, and it will be seen to consist of two antenna coils essentially back-to-back, with a two-gang tuning capacitor and a negative-mutual coupling coil (EL-56 on the schematic). The 1N34 Germanium diode serves as the detector, with the signal being developed across the resistor.

This tuner is designed for use in metropolitan areas where there are likely to be a number of radio stations within a radius of 20 to 25 miles, and when used with a good antenna from 75 to 100 feet in length will give an audio output ranging from .05 to 0.5 volts. Even with a shorter antenna, satisfactory results are obtained with an output of less than .001 volts, providing the signal is fed into a high-impedance microphone input channel of a high-quality amplifier.

The coils specified for this tuner are the products of J. W. Miller Co. of Los Angeles, and while a complete kit

range. For satisfactory results, it is necessary that high-Q coils be employed, and this requirement is fulfilled by the 242-A coils specified.

CATHODE FOLLOWERS

[from page 13]

has a data book transconductance of 9000 micromhos, and a mu of the order of 5000. With resistance coupling and reduced plate voltage we lose, but probably can still realize a transconductance of 5000. With a little computing we find promise of an output/input ratio of .98 to .99, and an output impedance of about 200 ohms.

Some Practical Matters

We are now ready to consider the design of the actual circuit, and its execution in a reasonably dependable assembly.

First, we must apply d.c. to the heater of the 6AC7. In spite of anything written to the contrary, a cathode follower with a.c. on the tube heater is full of hum. Rectified a.c. is permissible if the filtering is adequate, and if the heater is kept at ground potential to a.c. To avoid injuring the heater-to-cathode insulation we are then compelled to use a voltage divider and capacitor arrangement, with the heater at cathode potential for d.c. and at ground potential for a.c.

The plate supply voltage must be well filtered. Some papers have claimed that plate supply ripple is degenerated out in a cathode follower, and that poor power supply is permissible. Practical experience does not bear this out.

In laying out the input circuit, make it as short as possible. If you have too

much stray capacitance, it can be guarded out by a shield driven by the cathode, but good design will shorten the leads to a point where no guarding is necessary. Such driven shields are undesirable, because their capacitance to ground acts as an additional capacitive load on the follower output.

This brings us to the circuit itself. In its design, remember that the output will always be loaded with at least 100 μf of input cable and plug capacitance. If a shielded output cable is to be used, allow another 100 to 150 μf . Do not assume that the low internal output impedance of 200 ohms will make the follower immune to such loading, for it will not.

A representative circuit is shown in Fig. 6. Its input impedance with three feet of the cable previously discussed is 100 megohms and 6 μf . Performance curves are shown in Fig. 7. It is interesting to note that the output/input ratio is invariable up to a few volts below overload. In this connection it is significant to observe that when the ratio is of the order of 0.98 and 0.99 the distortion is too low to measure with ease. High quality oscillators are apt to have a harmonic distortion of 0.1 or 0.2 per cent which is of the same order as that which we are trying to measure. When the output/input ratio decreases, distortion begins to be sig-




Fig. 8. Harmonic distortion vs. voltage ratio of cathode follower.

nificant. Figure 8 shows that in the design given the ratio has remained virtually constant up to the point at which the distortion begins to increase rapidly.

In connection with measurement of very low distortion values, it is necessary to remember that a copper oxide voltmeter will generate distortion in the circuit to which it is connected, and that this distortion will be negligible only when the meter resistance



LIST PRICE
\$6750



Multi-Impedance Switch
for Low, Medium or High
Impedance.

THE FAMOUS "55" UNIDYNE DYNAMIC

Unidirectional Microphone. This superlative dynamic microphone is a Multi-Impedance Microphone—you can have either High, Medium, or Low Impedance simply by turning a switch! Because it is a Super-Cardioid, the "Unidyne" kills Feedback energy by 73%—making it possible to use under the most difficult acoustic conditions. The "Unidyne" is probably the most widely used microphone throughout the world. Recommended for all highest quality general-purpose uses.



THE NEW "737A" MONOPLEX CRYSTAL

Unidirectional Microphone. The "Monoplex" is the *ONLY* Super-Cardioid Crystal Microphone made. As such, it is undoubtedly the finest of all crystal microphones. (A comparative test will prove this statement convincingly.) The "Monoplex" employs the same type of acoustic phase-shifting network used in the highest cost Shure Broadcast Microphones. Has "Metal Seal" crystal—will withstand adverse climatic conditions. Can be used in those applications where severe background noise would make conventional microphones practically useless!

LIST PRICE
\$3975

Licensed under patents of Brush Development Company. Shure patents pending.

SHURE BROTHERS, Inc.

Microphones and Acoustic Devices

SHURE

225 West Huron Street, Chicago 10, Illinois • Cable Address: SHUREMICRO

A New Audio Instrument: THE BRIDGER

MODEL 100 BRIDGER—Connects a vacuum-tube voltmeter, distortion meter, and/or oscilloscope to a high-impedance circuit, such as an amplifier or counter, without loading it and changing the operating characteristics. A shielded cable may be used for eliminating hum without loading the circuit under test with the cable capacitance. Using an improved cathode follower and a specially designed double-shielded cable, the Bridger offers an input impedance of 100 megohms in parallel with 6 mmf at the end of a three-foot shielded cable, and an output impedance of 200 ohms.

MODEL 105 VOLTAGE DIVIDER—Extends input-voltage range to 250 volts when slipped on tip of the cable-probe of Bridger. Input impedance 50 megohms in parallel with 6 mmf; voltage ratio 10:1.

Miniature Preamplifiers For Use With 640AA Condenser Microphones

Model No.	Output for 1 dyne/cm ²	Output Z. ohms	Length, inches	Power Requirements			
				Plate E	Plate I	Fil. E	Fil. I
12	—40 dbm	250, bal.	10	135 v	2.2 ma	1.25 v	70 ma
14	—55 dbm	250, bal.	6½	135 v	2.2 ma	1.25 v	50 ma
16	1.5 mv, open ckt	500, unbal.	4½	300 v	3.0 ma	6.3 v	200 ma

Diameter, all models — 1¼ inches

MODEL 121 LOGGER

Logarithmic voltmeter with 50 db linear meter scale; output may be used to feed direct writing recorder (via a suitable amplifier) for acoustical reverberation tests. Input impedance—50,000 ohms; output impedance—1000 ohms.

Our wide acquaintance with new methods and unusual techniques is used to give improved performance at reduced cost.

AUDIO INSTRUMENT COMPANY

1947 Broadway

New York 23, N. Y.

MODEL 140 DISC-NOISE METER

Overload-proof amplifier voltmeter for quality control of lacquers, phonograph records, transcriptions. New stable logarithmic element. 20-db linear meter scale. Minimum reading 75 db below 7 cm/sec. velocity with pickup cartridge supplied.

is quite high compared to the circuit resistance. Otherwise, as much as 0.5 per cent distortion has been observed.

Higher Voltage Rating

A glance at Fig. 7 shows that the particular design illustrated in Fig. 6 is limited to input voltages of the order of 35 volts maximum. It is possible to make special designs for higher input voltages, by various obvious




Fig. 9. Voltage divider circuit.

means. In most cases, however, it is preferable to insert a voltage divider at the input to the cable.

In this circuit the voltage ratio at low frequencies is set by the resistance ratio. At higher frequencies the cable capacitance C_1 begins to change the accuracy of ratio. A small capacitor C_2 is therefore added across R_2 , and is adjusted to keep the ratio correct at higher frequencies.

The circuit which has been described promises to improve both convenience and accuracy of measurement in the audio laboratory by making it possible to bridge instruments across any part of a circuit with impunity.

RECORD REVUE

[from page 21]

province to suggest that these LP troubles are inherent in the system itself—maybe not. Still, my impression is that such difficulties should be less in the 45 than the wide-expanse LP recording. My feeling is, too, that whatever the reason, I will expect to find more uniformity between standard and 45-rpm versions of a recording than between standard and LP—the LP often differing markedly in one way or another from the standard. This impression may change with time.

After LP playing, the return to a changer has been unpleasant. I find the small records more clumsy in the unpacking, sorting, setting up and repacking than the standard records which lift easily out of their folders in an album. The changer is on the average slower at the breaks than my standard changer with its valuable velocity trip feature. The lack of a shut-off at the last record has fooled me time and again, when attention wandered a bit, into letting the top record repeat several times; one must keep constant mental count of the sides played in order to catch the machine before it begins that fatal repeat and this only accentuates the annoyance one feels at the same old musical breaks. (Again, this is the

YOU CAN
READ
THESE
ADVANCED
ENGINEERING
DETAILS OF

THE
ASTATIC
CLD

TURNOVER
PICKUP



Astatic Crystal Devices manufactured under Brush Development Co. patents

... But you will have to
LISTEN to it to know its
Excellence of Frequency Response

• The Astatic CLD Turnover Pickup gained immediate, widespread preference in the trade primarily for its outstanding excellence of frequency response, as revealed in comparative listening tests. You are urged, too, to make such tests... note particularly the response at low frequencies... then add this experience to your conclusions based on the following details. The CLD is engineered to play both slow speed and standard 78 RPM records at eight-gram needle pressure, thus has no extra mechanism to change pressure when knob is turned, eliminating a potential source of trouble and varying reproduction quality. It employs the Astatic LQD-1 Double-Needle Cartridge, with separate "Q" Needles which snap in and out individually with gentle pry or pressure of a penknife or other small instrument. Cartridge need not be removed from pickup or other operations performed in replacing needles. The CLD's output is 0.9 volts at 1,000 c.p.s. with 33-1/3 and 45 RPM Records; and 1.2 volts with 78 RPM Records. Mounts seven inches from turntable center, die-cast curved arm finished in dark brown Hamerlin. Available for prompt delivery.

THE
ASTATIC
CORPORATION
CONNEAUT, OHIO
IN CANADA: CANADIAN ASTATIC LTD. TORONTO, ONTARIO

classical record collector, the minority, speaking!) I have considerable trouble with the arm bouncing as it lands, amputating the opening passage. Even with brand new records I have already run into slippage and have seen a record stop entirely and refuse to turn at all. But note, these are minor troubles, annoying in present equipment but not impossible of correction—though why RCA didn't figure on a corrugated ring to lock the records together I can't for the life of me see. A better center-operating changer would be simple enough, though perhaps more costly; it should decidedly have an automatic stop after the final record and a gentler arm movement, whatever the cost. RCA should be able to lick the serious problems of warpage and slipping without too much difficulty. Beyond this, I don't see that complaints are easily made, except those that are irrelevant, such as those concerning the original recording. Ah yes—one more thought: the RCA records are at such a low level that plenty of gain is needed, often considerably more than with the LP record and thus all sorts of minor technical deficiencies are apt to be shown up in the input end of many outfits. True, ghosts and the like are avoided and the records may well play longer and easier. But is the sound better? Surface, too, rears its ugly . . . well, surface is a danger anyway.

And so we get back to the basic division between standard-play and long-play record and to one more—the matter of available repertory. Here there seems to be little more than pure policy decision. Columbia has delved widely and extensively into its past library to bring out enormous numbers of older recordings in LP form, covering every taste. RCA Victor, on the other hand, has made a preliminary catalogue mostly from popular classical favorites, best sellers, and has added only a tiny dribble of recent records to that catalogue since then. Why, is anyone's guess. Perhaps the older RCA records aren't up to the Columbias on 16-inch? If Capitol can dub the Telefunkens of years ago onto 45, surely RCA can find something in its catalogue to haul out? Apparently the policy has been set to issue new recordings only on 45. If so, I opine that such a policy is a mistake. On the other hand, it is quite true that the attraction of the RCA reissues is less than that of the LP's, since the advantages are confined to the size and convenience of the new record, with little other than improved surface noise in the actual sound. Same old breaks. The LP no-breaks advantage is, no getting around it, a sales point of the first magnitude not to be matched by the no-distortion argument—or so it seems to be, as I see it.

How long can all this last? Years, perhaps. But my own strictly private feeling is that there will have to be a deal, and that deal not so terribly far off, what with some rumored additions to bandwagons coming up. Meanwhile I shall continue to enjoy both 45's and 33's for what's on them—and that's a lot. I like music!

(May I remind readers that the viewpoints expressed above are strictly my own and in no way necessarily represent the attitude of the magazine itself or any of its offices. This is inserted at my own suggestion, not the editor's. E.T.C.)



When you've stretched your budget to the limit to buy the best equipment and still can't be sure of uniformly good recordings...

DON'T TAKE YOUR EQUIPMENT APART...



*Switch to
Presto Discs*

The Presto label on a disc means uniform high quality of mechanical and chemical properties... *always*.



World's Largest Manufacturer of Instantaneous Sound Recording Equipment and Disc.

PICKERING PICK-UP CARTRIDGES

- For the utmost in record playing pleasure
- For the greatest length of satisfactory service
- For those who want and demand the highest quality record reproduction, with all of the original modulation, realism and brilliance
- For minimum record wear
- For minimum extraneous and annoying sounds

120 SERIES for transcriptions and lacquer discs

MODEL R-150 for phonograph records

140 SERIES for microgroove records

All Pickering Pick-up Cartridges are available with either a Diamond or Sapphire Stylus. . . . Diamond Styli are good for thousands of playings whereas Sapphire Styli require replacement after a few hundred playings.

Pickering also manufactures Pick-Up Arms, Preamplifiers, Equalizer-Amplifiers and Equalizers.

PICKERING & COMPANY

Oceanside, New York

World-Wide Popularity

Since the inception of AUDIO ENGINEERING in May 1947, engineers and audio hobbyists have subscribed in ever-increasing numbers, not only in the 48 states and in all of the major foreign countries but in such places as Tasmania, Transvaal and Trinidad.

Each month AUDIO ENGINEERING covers the latest developments and practices in recording, reproduction and instrumentation for the entire audio field.

Subscribe Now—Don't Miss an Issue! Back numbers are hard to get!

AUDIO ENGINEERING
342 Madison Avenue, New York 17, N. Y.

Sirs: Here is my ☐ check (or ☐ money order) for \$..... Enter my subscription order to AUDIO ENGINEERING for the next..... issues. Subscription Price: In U.S.A., Canada and Pan American Union—12 issues \$3—24 issues \$5. All others \$4.00 per year. Please check one: ☐ New Subscription ☐ Renewal

Name (please print).....

Address..... City..... Zone..... State.....

Occupation (give title and department).....

Firm Name.....

Recent Recordings

Prokofieff, Scythian Suite (1914)
Philadelphia Orch. Ormandy.

Columbia LP: ML 4142(1/2) MM 827 (3)

● This is not quite the type of music ordinarily to be found on the month's best demonstration record, but once you've listened you'll see why it's bound to take a high prize. The music itself is far more complex but not outwardly so very different from the well-known Gayne suites of Khatchaturian (who, writing a quarter century later, was merely stealing somebody else's thunder). It is savage, primitive sounding music, full of fine thumpings and poundings in the bass and with brass and percussion galore in the upper ranges. Columbia has recorded it with these facilities placed well to the front—or so it sounds—and the result is a most gratifying bedlam sharp and clear! I haven't heard the standard version; the LP is terrific. (The Respighi Roman Festivals on the reverse, released on standard some time back, has some pretty good sounds in it too.) If you are curious as to how come Prokofieff was caught writing stuff like this, remember that at about the time of the first war there was a great rash of this kind of primitivism, in other arts as well as music, and almost every composer fell in line at least for a time. The "Sacre de Printemps" (Rites of Spring) of Stravinsky was the leading noise maker and is decidedly the best known example now; but even Stravinsky wrote others in the style—"Les Noces," for example. Prokofieff wrote a group of "barbaric" works, including the often-heard first violin concerto; but the pagan rite was not really his line and he left paganism for the more suave and polished music that we hear ordinarily from him. It is interesting that the well-known "Classical" symphony was written at about the same time as this utterly different music.

Gould, Spirituals for Orchestra.

New York Philharmonic, Rodzinski.

Columbia LP: ML 2042(1/2) MM 832 (3)

● This is no doubt a good many months old, since Rodzinski left New York a season ago but it rates with anything new so far available. The music—"classical", technically speaking—is the sort we have heard before from Gould, hard, dissonant, perhaps even embittered, avoiding a bit too carefully the pat and slinky harmonies of the popular style. Gould; one movement, inevitably, breaks down into a highly jazzy bit of humor and this may be the best of all, it being the most natural. Because of the colorfully dry orchestration (Gould is a master of that) this makes for a good demonstration record though the severity of the music perhaps will dampen the engineer's ardor. I have the standard version; the LP includes the word-and-music "Lincoln Portrait" of Aaron Copland on the reverse.

Mozart, Serenade #10 for 13 wind instruments, K. 361.

RCA Victor DM, WDM 1303 (4)

Bach, Suites #1 in C, #4 in D.

Boston Symphony Orch. Koussevitsky

RCA Victor DM, WDM 1307 (5)

● Results from the various recording sessions at Tanglewood, where the Berkshire Festival occurs with this orchestra each summer, have been curiously uneven. Some Tanglewood records have been by most critical accounts atrocious—the Beethoven Ninth Symphony for instance. Others, the above included, have turned out remarkably well. Probably due to different recording locations but in any case the Mozart and Bach items here which I have in the 45-rpm version, give forth an excellently sonorous

sound, spacious, with good sense of depth and perspective not to mention a modest but comely expanse of good highs. The Mozart succeeds an earlier RCA version (which RCA apparently forgot it owned—the publicity named this new one as the first in the RCA catalogue!) by Edwin Fischer, made 'way back, in Europe and sounding musically very much like this though omitting some of the music here recorded (V 743). There is a new European version I haven't heard, said by some to be better; I find the RCA new one a thoroughly adequate, straightforward rendering by a group of excellent musicians and would not be inclined to demand anything better. The music is the sort of gay outdoor type much favored in Mozart's day—it was the ancestor of the "German band"—but this is on a far meatier level (to make a strange metaphor) than most such serenade music and indeed is one of my favorite Mozarts. The long slow introduction to the first movement is the high point. The Bach suites come forth from the Koussevitsky factory a good deal better made than the Brandenburg Concertos also recorded at Tanglewood. Except for some dreadful slowings-down at the ends of movements, quite unwarranted, the playing here is straightforward and accurate and the Baroque splendor of the music comes through most effectively in the big, live RCA recording. Incidentally, the Bach album contains some of the most painful musical breaks, at the ends of the sides, I have yet to hear, rather unfortunate considering the present delicate situation, LP vs 45!

A good test of 45-rpm at its best by the way, is the reissue of Stokowsky's already well known Tchaikowsky "Sleeping Beauty" ballet music, WDM 1205. Quality-wise, you won't find much to complain of here. Watch out for a faint low-pitch hum (60 cps?) which I seem to detect in some of the 45's. Picked up at some stage in the dubbing?

Mendelssohn, Symphony #3 ("Scotch")

Chicago Symphony, Rodzinski.

RCA Victor DM 1285 (4)

● Here we catch up to the rapidly moving Rodzinski during his Chicago stay—he's left there by now. There's nothing in this that will make your Scotch blood tingle if you have any—it was this symphony that sent the slightly absent-minded Schumann into rhapsodies over its wonderful *Italian* atmosphere (he had accidentally mixed it up with number 4, the "Italian" Symphony); Scotch or not, you'll find it the best in easy expressive tuneful Mendelssohn, a well made and thoroughly pleasurable symphony, if not overly profound. The Rodzinski performance seems to me excellent and the RCA recording is good too, with acoustics perfectly suited to the music.

Scriabin, Poeme d'Extase

San Francisco Symphony, Monteux.

RCA Victor SM 1270 (2)

● If you like near-hysterical music, you'll like this (but some people call Wagner's "Tristan" hysterical; maybe you'd better judge for yourself!). You may ignore the complicated mysticism which is the Scriabin hall-mark; musically it doesn't matter much though historians may make much over his ideas, as he certainly did himself. What's interesting here is the similarity in the acid harmonies of this 1909 music to much of the early Stravinsky of shortly later—Stravinsky being, as far as anyone can say, the ultimate example of the hard-headed realist in music. This music is the kind of "ecstasy" that never lets down from beginning to end; its tautness fascinates some, bores others. Its performance by Monteux is a guarantee of the best; Monteux, the great French conductor has made his San Francisco Orchestra into one of the world's leading ex-

THE MCPROUD SPEAKER CHAMBER

With a good 15-inch speaker, effortless response to 37 cycles is easily achieved with unsurpassed purity of tone. The McProud corner cabinet provides the realism of reproduction so long sought after and now a fact.

As offered by Terminal, the McProud Chamber is supplied in knocked-down form, easily assembled with a screw-driver the only required tool. Finely grained selected hardwood veneers are used so that you may finish all surfaces to match your furniture or room decoration. It will take high gloss or waxed finishes beautifully.

Supplied for 2-way speaker systems or for 15" coaxial speakers. Complete with all hardware and instructions for easy assembly, **\$99.50** less speaker components

12" Now Available! The McProud Speaker Chamber for 12" speaker systems. Big speaker performance in a compact baffle design using same principle as in 15" model illustrated. Made of 5/8" fir plywood. Comes completely assembled, except for top which is easily fastened into place. Ample space is provided so that most types of tweeters can be mounted inside above the 12" low frequency speaker, cutout for tweeter not provided. 41" wide, 25" depth from corner, 30 3/4" high.

\$39.50 NET



FULL-RANGE LOUDNESS CONTROL This is the scientific loudness control based on the well-known Fletcher-Munson curves. These curves chart the frequency response of the human ear at various volume levels.

23-step control gives fine shading of volume. Easily connected in place of regular grid circuit volume control. Single hole mount. 3" long, 2 1/4" diameter, 1 1/2" shaft length. Conventional 3-terminal connection. Net price..... **\$9.95**

See article by John Winslow in February, 1949, Audio Engineering for interesting discussion on this loudness control.

CLARKSTAN 12" VINYLITE SWEEP FREQUENCY RECORDS

For use with oscilloscope, instantaneously shows the entire audio spectrum from needle point to output terminals of amplifier. Illustrates visually the effects of equalizing and tone control circuits. Indispensable for precision audio engineering.

102-M—33-1/3 rpm LP micro-groove frequency sweep from 70 to 10,000 cps = 1 db. with pips at 1, 3, 5, 7 and 10 Kc.

1000-A—78 rpm, 70 to 10,000 cps recorded flat within ± 1 db. Frequency marker pips, high level output.

1000-D—78 rpm, 5,000 to 15,000 cps, recorded flat within ± 1 db. Distinct frequency markers at 5, 7, 9, 11, 13 and 15 Kc. High level output. Your cost, each **\$6.60**


All records supplied with instructions and calibration charts for 3" and 5" oscilloscopes.

NEW THORDARSON WIDE RANGE AMPLIFIER

Model 32W10—Has frequency response of 20 to 20,000 cps, push-pull 10 watts audio power output with less than 2% distortion. Hum level is so low (70 db. below maximum output), that you'll find this amplifier one of the quietest and cleanest you've had the pleasure of listening to. Has input for tuner and crystal phono cartridge, with provision for plug-in preamplifier needed for new wide-range magnetic cartridges. A dual tone control provides separate bass and treble boost and attenuation, each control continuously variable for best response. Output impedances are 4, 8 and 16 ohms. Finish is attractive hammetone. Net price, **\$32.34**

complete with tubes.....

32W00—A preamplifier for plug-in to 32W10 amplifier. Provides proper frequency compensation for all popular magnetic wide-range cartridges, such as G.E., Pickering, Clarkstan, etc. Complete with tube, only..... **\$5.82**



FREE!

WRITE FOR YOUR COPY OF OUR NEW 1949 CATALOG OF HIGH QUALITY SOUND EQUIPMENT

TERMINAL
RADIO CORPORATION

Distributors of Radio & Electronic Equipment


85 Cortlandt St.-New York 7, N.Y. • Phone-WORth 4-3311 • Cable-Termradio

MERIT

NEWS

MERIT TRANSFORMERS Lead Again for Sound Equipment! with NEW OUTDOOR TYPE

Universal Line Transformers. To couple various line impedances to voice coil. Universal mounting bracket. Designed specifically for maximum service in the outdoor sound field. Features: Universal mounting (may be bolted or clamped to speaker bracket); Weather-sealed at moderate cost to withstand outdoor conditions; Encased in one piece drawn metal can; Potted to resist moisture absorption; Terminal board mounted inside can.



Mounting JO
Mtg. Center Case
2 3/4 x 3 1/8
Dimensions
H W D
4 1/4 4-7/16 3-9/16

TYPE NO.	LIST PRICE	OHMS IMPEDANCE	SEC. WATTS
A-4040	\$ 8.75	250-500-1000-1500-2000	4.8-16 8
A-4041	9.75	250-500-1000-1500-2000	4.8-16 12
A-4042	13.75	250-500-1000-1500-2000	4.8-16 25
A-4043	9.75	45-50	4.8 12

HEAVY DUTY OUTPUT TRANSFORMERS
High Level Type to Couple Line to Speaker
Sec. Impedances: 4.8-15-250-500 Ohms
OPEN MOUNTING D

TYPE NO.	LIST PRICE	TUBE	PRI. IMPEDANCE	PRI. M.A.	MAX. PER SIDE WATTS
A-3133	\$11.50	P.P. Par. 6L6, P.P. 807	3300 c.f.	240	55
A-3131	7.00	PP6L6, 6Y6, PP2A3, 6A3, 6B4, 45, PP6N7, 46	5000 c.f.	80	30
A-3128	8.00	PP6V6, 6F6	8000 c.f.	50	14
*SEALED-IN MOUNTING H					
A-4033	16.50	P.P. Par. 6L6, P.P. 807	3300 c.f.	240	55
A-4030	13.00	P.P. 6L6	6600 c.f.	80	34
A-4028	12.00	PP6V6, 6F6	8000 c.f.	50	14

*Weatherproofed, potted for outdoor use at 100% over list price.



For information on other transformers see the complete MERIT line in Sam's Red Book or ask for New MERIT Catalog No. 4911



EQUIP WITH MERIT OUTDOOR TYPE TRANSFORMERS TODAY



ANNIVERSARY 25



COIL & TRANSFORMER CORP.

4415 NORTH CLARK ST., CHICAGO 40, ILL.

ponents of French orchestral music. Strange things happen in California!

Schumann, Manfred Overture; Beethoven, Consecration of the House Overture. NBC Symphony, Toscanini.

RCA Victor DM, WDM 1287 (3)

• If you have a yen for something by Toscanini, pass up the Tchaikovsky 6th symphony and try this. To my ear at least this is about his best album with the NBC to date. Both overtures benefit from the well known Toscanini drive, since both—each in its own way—are a bit heavy handed. Toscanini makes 'em get up and go and the real stuff in both comes through superbly. Moreover, again to my ear, the recording itself is better, more natural with better highs and bigger liveness than the Tchaikovsky 6th recording. Don't ask why. (See last month for review of the Tchaikovsky, WDM 1281 and DV 27.)

For those who haven't caught on yet... the "W" records from RCA Victor, with same numbers for the albums as the standard, are 45 rpm issues. Single 45's, alas, have entirely different numbers from their 78 counterparts. Columbia LP's are renumbered, with 12-inch records in the 4000 series and ten-inch in the 2000. Columbia slow speed singles, 7-inch, also have different numbers from the 78 counterparts.

Beethoven, Violin Sonata #1 in D, opus 12; Schubert, Violin Sonata #1 in D, opus 137. Joseph Szigeti, violin, with V. Horowitzki, Andor Foldes.

Columbia LP: ML 4133

• A new recording and a quite old one of two sonatas which coincidentally have the same numbers and keys. The old one is the Schubert, a well known recording in its original shellac pressing; it is one of those improved LP reissues, going back to re-dub the original 16-inch master (though there seems to be some wavering in pitch that shouldn't be present). The new one is the Beethoven, and the comparison is quite interesting: the new recording is far sharper in the highs than the old, though both have adequate tonal range—it is as though the characteristics to 10,000 were radically different in the two. The new one has considerable preemphasis the old has relatively little, if any. Just how this comes about I do not know, but that is indubitably the effect, and other new-old LP couplings show similar contrasts. With equalization by ear, one can get the two to sound very much alike. Interesting that in the new Beethoven recording Szigeti exhibits a wallowing wobble that is entirely absent in the old Schubert, of eight or ten years ago. Does he realize it himself, I wonder? Both are excellent performances of genuinely listenable music—if, again, you can take violin and piano. Of the two, the Schubert is the most catchy for the inexperienced ear—like so much Schubert, it grows on you fabulously once the tunes are embedded. (Neither of these recordings is up to the Decca ones reviewed above, good as they are. Note that in the Beethoven, Szigeti can again be heard breathing, so close is the mike, so wide the tonal range!)

Haydn, The Musical Clocks.

E. Power Biggs, organist

RCA Victor 49-0419 (7") 10-1471 (12")

• These compete for the Shortest Pieces Ever Written—they were designed for the musical clocks that were the scientific marvels (and true ones, too) of the 18th century. Biggs plays them on clock-like stops in the organ. There are eight of them on one record. It's real music, too.

PROFESSIONAL DIRECTORY

C. J. LeBEL
AUDIO CONSULTANT

Sound Recording • Instrumentation

370 RIVERSIDE DRIVE
NEW YORK 25, N. Y.

Winston Wells

Designer and Consultant

Acoustical, Electronic and Nuclear Research

307 East 44th St.

MU 4-3487

New York 17, N. Y.

Custom-Built Equipment

U. S. Recording Co.

1121 Vermont Ave., Washington 5, D. C.

STerling 3626

Consultation • Design • Fabrication

Audio Facilities Corporation

608 Fifth Avenue

New York 20, N. Y.

RATES FOR
PROFESSIONAL CARDS
IN THIS DIRECTORY

\$10 Per Month.
Orders Are Accepted
for 12 Insertions Only

HERMAN LEWIS GORDON

Registered Patent Attorney

Patent Investigations and Opinions


Warner Building
Washington 4, D. C.
NAtional 2497

100 Normandy Drive
Silver Spring, Md.
SHepherd 2433

NEW PRODUCTS

• **"Broadcast Station Measurements"** is the title of 38-page booklet offered by Hewlett-Packard Company, 395 Page Mill Road, Palo Alto, Calif., free to all radio station chief engineers. It gives full information on making measurements required by amendment (e) to Section 3.46 of "Standards of Good Engineering Practice." This "how-to-do-it" manual states the requirements for both AM and FM broadcasters, lists the equipment necessary to make the measurements, and gives detailed procedures for measuring, recording, and tabulating the information in a manner which will be acceptable to the F.C.C. Included in this company's line are most of the test instruments necessary for making the required measurements.

• **The Model 140 Disc-Noise Meter** is the first commercially available device for checking noise level of lacquer discs and test pressings. Disc Recording companies have long needed some method for making these measurements, and improvised arrangements often resulted in inaccuracy and




in damaged meters. The unit consists of a high-gain preamplifier, a new logarithmic circuit, and a v-t voltmeter so arranged that the indicating instrument is overload proof. The logarithmic circuit permits the use of a linear db scale, covering a range of 20 db, and the instrument itself has the same ballistic characteristics as the standard VU meter. Information: Audio Instrument Co., 1947 Broadway, New York 25, N. Y.

• **Simplex Tape Splicer** is the logical answer to the requirement for a low priced unit for making a splice in magnetic tape quickly and easily. Uses a non-magnetic block to avoid degradation of the recorded



material during the splicing operation and accurate machining ensures a straight, true joint which is stronger than the tape itself. The unit is available from Burnett Service Co., 178 W. 168th St., New York 52, N. Y.


NOW YOU CAN AFFORD THE SPEAKER YOU HAVE ALWAYS WANTED!



**PRICE
REDUCED 18%**

on the famous
**ALTEC 604B
DUPLEX SPEAKERS**

You benefit from increased demand, and resultant manufacturing economies! Not one iota reduction in the quality of the speaker — the speaker you have always wanted! But you get it for 18 percent less!



**PRICE REDUCED 16%
ON THE ALTEC 600B
DIA-CONE SPEAKER**

Utilizes the famous dia-cone principle of high-frequency reproduction. Ideal for PA, home, 16 MM and industrial uses. Quality remains the same — you save 16 percent on price!


YOUR DEALER HAS THESE NEW PRICES!

161 Sixth Ave., New York 13, N.Y.
1161 N. Vine St., Hollywood 38, Calif.



IN THE PROFESSION, AN HONORED NAME

VU and DB Indicators



Cinema Type 6719-C

... For instantaneous comparison and continuous check adjacent to magnetic tape recorders. Broadcasters and Recorders alike are finding Cinema Volume Unit Indicators a convenient necessity. New recessed meter faces. Meter scales available in either "VU" or "MODULATION" top scale. All adjustments available from front of panel. Complete with series resistance fine adjustment for extreme accuracy of readings.

Available in relay rack panels and cabinets in a choice of ranges. Cinema Decibel Volume Indicators come in a choice of ranges, too.


Write us of your requirements—we have a complete line of audio engineering supplies and many "hard-to-get" items available for immediate delivery.



CINEMA ENGINEERING COMPANY
1510 WEST VERDUGO AVENUE, BURBANK, CALIFORNIA

Export Agents: Frazer & Hansen, Ltd. • 301 Clay Street • San Francisco, Calif., U. S. A.

**BETTER COMPONENTS BUILD
BETTER REPUTATIONS**



SPECIFY El-Menco

No product is better than its weakest component. That's why more and more manufacturers specify El-Menco — the mica capacitor that always gives customer satisfaction and builds better reputations.

CM 15 ($\frac{1}{2}$ " x $\frac{1}{8}$ " x $\frac{3}{16}$ ")
For Radio, Television, Other Electronic Applications
2 to 420 mmf. capacity at 500 VDCw
2 to 525 mmf. capacity at 300 VDCw
Temp. Co-efficient ± 50 parts per million per degree C for most capacity values.
6-dot standard color coded.

CM 20 Available in "A", "B", "C" and "D" characteristics
2 to 1500 mmf. intolerances down to $\pm 1\%$ or .5 mmf. at 500 D.C. working voltage
6-dot color coded *Whichever is greater

CM 35 Available in "A", "B", "C", "D" and "E" characteristics
Minimum tolerance 1%
500 D.C. working voltage
6-dot color coded

ARCO ELECTRONICS

Sole agent for jobbers and distributors in U. S. and Canada.

135 Liberty St., New York, N. Y.

Write, on firm letterhead, for samples and catalog.

THE ELECTRO MOTIVE MFG. CO., INC.

Willimantic, Connecticut

THE NOW-ESTABLISHED

HARTLEY-TURNER 215 SPEAKER

These monthly messages can give no detailed idea of the exceptional growth in the number of Hartley-Turner fans in America. We are human enough to feel a warm glow at every letter which tells us how the 215 Speaker has brought a new thrill and pleasure to the writer. If high-fidelity, real high-fidelity, means anything to you, you can capture that same excellent reproduction for a very modest figure.

Rising costs in Britain have meant an increase in price, but still the price is far below what you would expect to pay for reproduction distortionless so far as the speaker is concerned. Those who could hardly believe our first claims, but took a sporting chance on our integrity, are now satisfied that we know a thing or two about speakers, but are still mystified at the performance-price factor.

Anyhow, the price is now \$50.00, which includes postage, packing and insurance. You pay the postman \$7.50 import duties, and you have then got something which your friends will envy.

Descriptive literature is free for the asking, but we do suggest you send us a dollar bill for "New Notes in Radio", a complete pocket guide to high-fidelity, and a regular supply of data sheets to keep you abreast of what we are doing. Our activities are confined to high-fidelity, but they do cover every aspect of the subject.

H. A. HARTLEY Co., Ltd.

152, HAMMERSMITH ROAD,
LONDON, W. 6, ENGLAND

**ADVERTISING
INDEX**

Altec Lansing Corp.	39
Ampex Electric Corp.	Cover 3
Arnold Engineering Co.	7
Astatic Corporation	34
Audak Company	32
Audio Development Company	31
Audio Devices, Inc.	Cover 2
Audio Facilities Corp.	38
Audio Instrument Company	34
Burnett Service Company	30
Camera Equipment Co.	28
Cinema Engineering Co.	39
Electro Motive Mfg. Co., Inc.	40
Electro-Voice, Inc.	27
Fairchild Recording Equip. Corp.	29
Gordon, Herman Lewis	38
Hartley, H. A. Co., Ltd.	40
Harvey Radio Company, Inc.	30
Hewlett-Packard Co.	2
Hollywood Sound Institute	40
Jensen Manufacturing Co.	10
LeBel, C. J.	38
Livingston Electronic Corp.	40
Merit Coil & Transformer Corp.	38
Pickering & Co., Inc.	36
Presto Recording Corp.	35
Professional Directory	38
Radio Corp. of America (Broadcast Equip. Div.)	4,5
Reeves Soundcraft Corp.	9
Shure Brothers, Inc.	33
Sylvania Electric Products Inc.	1
Terminal Radio Corp.	37
Triad Transformer Mfg. Co.	8
United Transformer Corp.	Cover 4
U. S. Recording Co.	38
Vibration Systems, Inc.	40
Wells, Winston	38

AUDIO ENGINEERING SCHOOL

A Practical Audio Engineering course in Sound Fundamentals; FILM, MAGNETIC and DISC Recording; Transmission Measurements; Monitoring and Mixing. Laboratories contain: Transmission Sets, Oscillators, Distortion Sets; Harmonic Analyzer; Intermodulation Analyzer and other eqpt. Recording Studio assimilating Broadcast, Motion Picture and Commercial Sound Recording. H. M. TREMAINE, Pres-Dir.

Approved for Veterans and Foreign Visas
HOLLYWOOD SOUND INSTITUTE Inc
1040-A No. Kenmore Hollywood 27, Calif.

VERTICAL LATERAL

REPRODUCERS RECONDITIONED
Types 9-A, 9-B, D-93306, MI-4856, MI-4875-G
Complete Stock of New Replacement Parts for All Types

This service is being used by leading radio stations and wired music companies from coast to coast. Factory prices prevail.


VIBRATION SYSTEMS, INC.
1040 W. Fort St. Detroit 26, Michigan

**Another Audio Addition
by
LIVINGSTON**



The Pocket Stylus Pressure Gage—with expanded 0-10 gram range and full range at 30 grams, is an economical yet accurate solution to the problem of stylus pressure determination.

Compact, sturdy, and attractive, this gage really "does the job." Selling for \$1.50 net, it's another member of the Line "by Livingston."



The MB Loudness Control is now available at most jobbers, and is the instantaneous hit we had hoped it would be.

Write us direct, if you care to, for the address of your nearest jobber.

Livingston Electronic Corp.
Livingston, New Jersey

**Ready NOW
ULTRASONIC FUNDAMENTALS**

By S. YOUNG WHITE

The rapid increase in the use of ultrasonics during the last few years makes it natural that the well-informed sound engineer should want to learn something of the applications and potentialities of this amazing new field. But interest in ultrasonics is not confined to the sound engineer—it is of still greater importance to the industrial engineer for he is the one who will visualize its uses in his own processes.

Elementary in character, ULTRASONIC FUNDAMENTALS was written originally as a series of magazine articles just for the purpose of acquainting the novice in this field with the enormous possibilities of a new tool for industry. It serves the double purpose of introducing ultrasonics to both sound and industrial engineers. The list of chapter headings will indicate how it can help you.

CHAPTER HEADLINES

Too Much Audio. Opportunities in Ultrasonics. Elements of Ultrasonics. Experimental Ultrasonics. Coupling Ultrasonic Energy to a Load. Ultrasonics in Liquids. Ultrasonics in Solids. Testing by Ultrasonics. High-Power Ultrasonics. Notes on Using High-Power Ultrasonics. Applications of Ultrasonics to Biology. Economics of Industrial Ultrasonics.

The applications of ultrasonics have already extended to many industries, and as its possibilities are explored they will increase a hundredfold. To keep abreast of its growth, engineers in all fields must know what they may expect from ultrasonics, how it is used, how the energy is generated, and the techniques of applying ultrasonic treatment to many processes.

ULTRASONIC FUNDAMENTALS is not a big book—it does not cover the entire field of ultrasonics with hundreds of pages of dull reading. But in the three hours it will take you to read it, you will get a down-to-earth glimpse into the far-reaching possibilities of a new art.

ULTRASONIC FUNDAMENTALS

By S. YOUNG WHITE

36 pages, 40 illustrations. $8\frac{1}{2}$ x 11, paper cover. **\$1.75**

Book Division, Dept. A
RADIO MAGAZINES, INC.


342 Madison Avenue
New York 17, N. Y.

Listen for the words "Transcribed by AMPEX" after the great shows in radio

Here's why.....
the new series 300
AMPEX
MAGNETIC TAPE RECORDER
answers industry need!



*Designed by engineers
who had your engineering
needs in mind!*



Portable model

Console Model 300* \$1,573.75

Portable Model 300 \$1,594.41

Rack Mounted \$1,491.75

*Meter panel extra

F. O. B. Factory, San Carlos, Calif.

★ **Original program quality preserved**

Use of independent reproduction facilities allows instantaneous monitoring and makes possible the most stringent comparisons between recordings and originals.

★ **Tape and playback noise non-existent**

Use of special record and bias circuits has eliminated tape noise.* Extreme care has been exercised to eliminate hum pick-up.

★ **Editing made easy**

With Ampex editing is almost instantaneous. Single letters have been actually cut off the end of words. Scissors and scotch tape are all the tools needed.

★ **You can depend on Ampex**

Read what Frank Marx, Vice President in charge of Engineering, American Broadcasting Company, says: "For the past two years A.B.C. has successfully used magnetic tape for rebroadcast purposes... A.B.C. recorded on AMPEX in Chicago... 17 hours per day. For 2618 hours of playback time, the air time lost was less than 3 minutes: a truly remarkable record."

SPECIFICATIONS

FREQUENCY RESPONSE:

At 15" ± 2 db. 50—15,000 cycles
At 7.5" ± 2 db. 50— 7,500 cycles

***SIGNAL-TO-NOISE RATIO:** The overall unweighted system noise is 70 db. below tape saturation, and over 60 db. below 3% total harmonic distortion at 400 cycles.

STARTING TIME: Instantaneous. (When starting in the Normal Play mode of operation, the tape is up to full speed in less than .1 second.)

FLUTTER AND WOW: At 15 inches per second, well under 0.1% r.m.s., measuring all flutter components from 0 to 300 cycles, using a tone of 3000 cycles. At 7.5 inches, under .2%.

Manufactured by Ampex Electric Corporation, San Carlos, Calif.

DISTRIBUTED BY

GRAYBAR ELECTRIC CO. INC.


420 Lexington Avenue, New York 17, N. Y.
(Offices in principal cities)

**AUDIO & VIDEO
PRODUCTS CORPORATION**

1650 Broadway
New York, N. Y.

BING CROSBY ENTERPRISES

9028 Sunset Blvd.
Hollywood 46, Calif.



for every application


While the catalogue line of UTC components covers a wide variety of applications, many people are not familiar with the full range of products produced by UTC. It is impossible to describe the thousands of special UTC designs as they become available. The illustrations below are intended to indicate some of the range in size of these special products.

A This 100 cubic foot modulation transformer is for 50 Kw. broadcast service. Frequency response flat from 30 to 20,000 cycles.

B The high Q toroid coil shown is 12" in diameter. It operates in a 50 Kw. circuit at supersonic frequency.

C This sub-miniature (.18 cubic inch) output transformer is intended for hearing aid and other extreme compact service. While the dimensions are only 7/16" x 9/16" x 3/4", the fidelity is ample for voice frequency requirements.

D This sub-miniature (.18 cubic inch) permalloy dust core toroid is available in a wide range of inductances, and for frequencies from 1,000 cycles to 50 Kc.



United Transformer Co.

150 VARICK STREET NEW YORK 13, N. Y.
 EXPORT DIVISION: 13 EAST 40th STREET, NEW YORK 16, N. Y., CABLES: "ARLAB"

write for catalog PS-409